



Flybook[®]
The Ultimate in Mobility

Flybook V5 User's Manual

V5W1BB (without 3G)





V5W1BBHA (with 3G)












Dialogue Technology Corporation

Version 1.0, Jan.. 2007

DIALOGUE







Preface

Copyright and Safety Notices






Please read this section before using your computer.
Retain this manual for future reference.

Copyright

This publication, including all photographs, illustrations and software, is protected under international copyright laws, with all rights reserved. Neither this manual, nor any of the material contained herein, may be reproduced without written consent of the manufacturer.

Disclaimer

The information in this document is subject to change without notice. The manufacturer makes no representations or warranties with respect to the contents hereof and specifically disclaims any implied warranties of merchantability or fitness for any particular purpose. The manufacturer reserves the right to revise this publication and to make changes from time to time in the content hereof without obligation of the manufacturer to notify any person of such revision or changes.



Preface

Trademark Recognition

Bluetooth is a trademark of the *Bluetooth SIG, Inc.* (Special Interest Group). The *Bluetooth* trademark is owned by *Bluetooth SIG, Inc. USA*. *BlueSoleil* is a trademark of IVT Corporation. *Dialogue Technology Corporation* is a registered trademark. *FlyBook* is a trademark of the Dialogue Technology Corporation. *Windows* is a registered trademark or trademark of Microsoft Corporation in the United States and/or other countries. All other product names used in this manual are the properties of their respective owners and are acknowledged.

Federal Communications Commission (FCC)

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment onto an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Shielded interconnect cables and a shielded AC power cable must be employed with this equipment to ensure compliance with the pertinent RF emission limits governing this device. Changes or modifications not expressly approved by the system's manufacturer could void the user's authority to operate the equipment.

Declaration of Conformity

This device complies with part 15 of the FCC rules. Operation is subject to the following conditions:

- This device may not cause harmful interference, and
- This device must accept any interference received, including interference that may cause undesired operation.

FCC Caution

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

The antenna(s) used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Enabling wireless LAN and wireless WAN simultaneously in one computer is not allowed . While one is in use, the other will be turned off.

Running wireless devices in the aircraft is prohibited. Make sure all wireless devices in your computer are turned off during the flight.



Preface

FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20 cm (8 inches) between the radiator and your body.

FCC Wireless Regulation

Due to the FCC regulations, wireless LAN and wireless WAN modules shall not work in a machine simultaneously. If these two modules are installed in the V5, while one is in use, the other will be off automatically by the system.

Battery Caution

Danger of explosion if battery is incorrectly replaced. Replace only with same or equivalent type recommended by the manufacturer. Discard used batteries according to the manufacturer's instructions.


About This Manual

This User's Manual provides information to help you operate and get the most from your Flybook V5. Read the Quick Start Guide to quickly set up and begin using your computer.

Please read "[Copyright and Safety Notices](#)" on page i before using your computer.

Taking Care of the Flybook V5

After you unpack your computer, store the packing materials in case you want to ship the computer or if you have to return it for servicing.



Preface






Your notebook computer is a precision instrument that should be handled with care. Use common sense and follow the guidelines below, and your computer will last you for many years.

Do's and Don'ts with the Flybook V5

- Do not twist the display counterclockwise.
- Do not place heavy objects such as books on the computer.
- Do not use the Flybook V5 near water or a heat source such as a radiator.
- Do not expose the computer to temperatures above 50° C or below 0° C.
- Keep the computer away from direct sunlight or heat sources.
- Do not expose the computer to rain or moisture.
- Do not spill water or any other liquid on the computer.
- Do not place the computer near magnetic fields.
- Avoid subjecting your computer to heavy shocks or vibrations.
- Do not expose the computer to dusty or dirty environments.
- Do not place the computer on uneven surfaces.
- Do not cover the air vents around the computer.
- Only use the AC adapter that is provided with your computer.



Safety Information

The Flybook V5 has been designed and tested to meet the most recent standards of safety in notebook technology equipment. To ensure safe use of the Flybook V5, refer to the following safety instructions and any caution or warning messages on the equipment or in the user manual.






Preface

- 
- 
- Read and follow all instructions marked on the Flybook V5 and in the user manual before operating the V5. Store all safety information in a secure place for future reference.
 - Always set the Flybook V5 on a stable surface.
 - Only operate the Flybook V5 from the type of power source indicated on the rating label on the AC adapter.
 - Ensure all ventilation openings are not blocked or covered. Keep an adequate space (around 6 inches or 15 cm) around the Flybook V5. Never insert objects of any kind into the ventilation openings.
 - When using an extension cord with the Flybook V5, ensure that the total ampere rating on the equipment connected to the cord does not exceed the extension cord ampere rating maximum value.
 - Only use the supplied power cord. Do not place anything on the power cord. Place the power cord where it will not be in the way of foot traffic.
 - Always unplug any modem, LAN, or power cables from the Flybook V5 before you clean it.

Warning! The safety strap is only to prevent dropping the V5. It is not designed for carrying the V5.

- When using the Flybook V5 in tablet mode, use the safety strap to avoid dropping the Flybook V5.



Contacting Service

Disconnect the Flybook V5 from power and contact qualified service personnel if any of the following occurs:

- The power cord or adapter is damaged.
- Liquid has been spilled on the Flybook V5
- The Flybook V5 does not operate correctly when operating instructions are followed.
- The Flybook V5 has been dropped, or the case is broken open.
- Flybook V5 performance is seriously degraded.

If service is required, contact a sales representative or a local service center, or go to <http://www.dialogue.com.tw> for service information.



Preface

Warning! Before cleaning the computer, turn it off, unplug the AC adapter, and then remove the battery.

Caution: Do not wipe the keyboard, pointing device, pointing device buttons, or fingerprint reader with a damp cloth.

Cleaning the Flybook V5



Follow these instructions when cleaning the Flybook V5.

- Wipe the display with a clean soft cloth.
- If you use a mild glass cleaner to clean the display, spray a little on the cloth and then wipe the display. Do not spray cleaner directly onto the display.
- Clean the outside of the computer case with a soft cloth. You can moisten the cloth with a non-alkaline detergent.
- Use a vacuum cleaner to clean dust from the keyboard.






Table of Contents





Preface	i
Copyright and Safety Notices	i
About This Manual	iv
Taking Care of the Flybook V5	iv
Introducing the Flybook V5	1
Taking a Tour of the Flybook V5	3
Front-Left View	3
Rear View	7
Using the V5 in Clamshell Mode and Tablet Mode	9
Using the V5 in Clamshell Mode	9
Using the V5 in Tablet Mode	10
Getting Started with the Flybook V5	13
Battery Installation	13
Connecting the AC Adapter	16
Powering on the V5 for the First Time	16
LED Descriptions	17
Using the Fingerprint Reader	19
Using Flybook V5 Input Devices	21
Using the Pointing Devices	22
Using the Stylus	23
Using the Keyboard	24
Using Flybook Control Center	29

Opening the Control Center	30
Using the Control Center	31
Customizing the V5 Display	35
Connecting Devices	37
Connecting Audio Devices	37
Connecting USB Devices	39
Connecting an External Display	40
Connecting to a TV	41
Using an ExpressCard	42
Securing Your V5	45
Before You Go Online	45
Installing a Firewall	45
Installing a Spyware Blocker	46
Connecting Local Area Networks	47
Connecting a LAN	47
Connecting a Wireless LAN (WLAN)	48
Using the Built-in Modem	49
Making a Dial-up Connection	49
Sending and Receiving a Fax	51
Using the Built-in WWAN Module	53
Installing the SIM Card	54
Connecting the V5 to a Wireless WAN	55
Using GPS	59
Using the Built-in Webcam	61
Enabling the Webcam	61
Adjusting the Webcam Orientation	62
Managing System Power	63



Customizing the System BIOS	65
Accessing the BIOS Setup	65
Updating the BIOS Firmware	66
Troubleshooting	67
Identifying Problems	67
General Hardware Problems	68
Having the V5 Serviced	71
Specifications	73
Index	77






1

Introducing the Flybook V5

Congratulations on purchasing the Flybook V5! The Flybook V5 supports both Windows XP and the newest member of the Windows operating system family, Windows Vista.

The V5 is a powerful mobile computer which performs dual duty as a notebook or tablet computer. Advanced networking features include WLAN, WWAN, Bluetooth, and even an internal modem.



1 **Introducing the Flybook V5**

The Flybook V5 uses a pointing device with mouse buttons on both sides of the unit and a clickable scroll bar for added convenience. The LCD monitor can be rotated and laid flat to enable you to use the Flybook V5 as a tablet computer. Using the stylus, you can write text and draw on the tablet as you would on conventional paper.

The built-in webcam enables you to be seen by contacts using Windows MSN or other messaging software. The camera can be rotated 225 degrees for maximum flexibility.

The powerful Li-ion rechargeable battery provides more than 3 hours of mobility, making the Flybook V5 the best choice for people on the go.


2

2

Taking a Tour of the Flybook V5

This section describes the major components of your new Flybook V5.

Front-Left View



2 Taking a Tour of the Flybook V5

1. Status LEDs

- These LEDs display when the AC adapter is connected, when the HDD is being accessed, or when the WWAN, WLAN, or Bluetooth is activated.

2. Pointing device buttons (right)

- These pointing device buttons emulate mouse right and left buttons. The top button corresponds to a mouse right button. The lower button corresponds to a mouse left button. Refer to [“Using Flybook V5 Input Devices” on page 21](#) for more information.

3. Scroll bar

- This bar enables you to scroll up and down in web pages or word processing software. Refer to [“Using Flybook V5 Input Devices” on page 21](#) for more information.

4. Stick pointer device

- The Stick Pointer moves the cursor in the direction of the pressure you apply with your finger.

5. RF kill switch

- Wireless transmission uses power. Use this button to disable the wireless feature of your computer to save power or when instructed to do so, for example on an aircraft.

6. Fingerprint reader

- When you set up fingerprint authentication, you can use the fingerprint reader to turn on the computer. In addition to logging in to the computer, the fingerprint can control access to some applications.

Taking a Tour of the Flybook V5 **2**

7. Power button

- Press and hold the power button for two seconds to turn on the computer.

8. Left speaker

- Stereo speakers are built into the computer. The right speaker is on the opposite side of the V5.

9. Pointing device buttons (left)

- These pointing device buttons emulate mouse right and left buttons. The right button corresponds to a mouse right button. The left button corresponds to a mouse left button. Refer to [“Using Flybook V5 Input Devices” on page 21](#) for more information.

10. AC power connector

- Connect the AC adapter to this connector.

11. Middle mouse button

- This button corresponds to the center button on a conventional mouse.

12. Stereo Microphones

- Use the built-in stereo microphones for recording sound or video conferencing with friends.

13. Webcam and webcam LED

- Use the built-in webcam for video conferencing with friends. The LED indicates when the camera is active






2 Taking a Tour of the Flybook V5

14. Ambient light sensor

- This sensor detects ambient light and reduces screen brightness to adjust for optimum display quality.


15. Stylus slot

- Use the stylus in place of the mouse to interact with the Flybook V5.



Taking a Tour of the Flybook V5 **2**

Rear View



1. RJ-11 modem jack

- Connect a phone line to this jack to use the internal modem.

2. Ethernet connector

- Connect the computer to your home or office network (LAN) with the Ethernet connector.

3. Monitor (VGA) connector

- Connect an external display or projector to the monitor connector.

4. TV connector

- Connect a TV to this connector to use the TV as an external display.

5. Headphone jack

- Connect headphones or external speakers to the headphone jack.



2 Taking a Tour of the Flybook V5

6. Microphone jack

- Connect a microphone to the microphone jack.

7. USB connectors

- Connect USB devices such as printers or flash drives to the USB connectors.

8. Air vent

- Air vents help to prevent the interior of the computer from overheating. Do not block the air vents.

9. Strap slot

- This slot enables you to attach a strap to avoid accidentally dropping the V5.

10. ExpressCard slot

- Install an ExpressCard in the ExpressCard slot.



8

3


Using the V5 in Clamshell Mode and Tablet Mode

The Flybook V5 can be operated in Clamshell mode as a standard notebook or in tablet mode, enabling you to use the V5 as you would a tablet computer.


Using the V5 in Clamshell Mode

Follow these steps to use the V5 in clamshell mode.

1. Open the display.



2. Adjust the display to a comfortable viewing angle.



3 Using the V5 in Clamshell Mode and Tablet Mode


Using the V5 in Tablet Mode

Caution: Take care when adjusting the display not to twist or force the display to an extreme angle. See [“Do’s and Don’ts with the Flybook V5” on page v.](#)


Note: You can adjust the tilt of the display to adjust for glare, sunlight and other environmental factors to provide optimum viewing.

Follow the steps below to use the V5 as a tablet computer.

1. Open the display.



2. Tilt the display forwards until it is vertical.




Using the V5 in Clamshell Mode and Tablet Mode **3**

Caution: Do NOT twist the display counterclockwise. You will damage the LCD display.

3. Twist the display clockwise 180 degrees.




4. Flip the screen down as shown.



3 **Using the V5 in Clamshell Mode and Tablet Mode**

The Flybook V5 can now be used as a tablet computer.



4

Getting Started with the Flybook V5


This chapter explains how to install and charge the battery, how to connect the AC adapter, and how to power up the V5 for the first time.

Battery Installation

When your Flybook V5 ships, the battery is not installed. This section explains how to install the battery.

Using the Battery Lock

There are two latches for securing the battery in place: the battery lock (**B**) and the battery release (**A**).





4 Getting Started with the Flybook V5


Warning! Always close the battery lock after inserting the battery. If the battery lock is not closed, the battery could fall out when carrying the computer and cause injury or damage the battery.

The battery lock must be manually closed. The battery release is spring loaded and closes automatically when you insert the battery.

Installing the Battery


1. Slide the battery lock to the unlocked position .
2. Align the guides on the sides of the battery with the guides in the bay and then install the battery.





3. Slide the battery lock to the locked position .

Getting Started with the Flybook V5 **4**

Removing the Battery

1. Slide the battery lock to the unlocked position .



2. While holding the battery release in the open position , remove the battery.


Charging the Battery

The first time you charge the battery, you should charge it for eight hours. Thereafter, the standard charging time is about three hours. To charge the battery, install it in the computer (see [“Installing the Battery” on page 14](#)) and then connect the AC adapter (see [“Connecting the AC Adapter” on page 16](#)).

4 Getting Started with the Flybook V5

Connecting the AC Adapter

1. Connect the AC cable (A) to the AC adapter.



2. Connect the other end of the AC cable (B) to an electrical outlet.
3. Connect the AC adapter (C) to the AC jack on the computer.
The battery charge LED lights.

Powering on the V5 for the First Time


For information on turning on the Flybook V5 for the first time, refer to the bundled booklet entitled **Windows Start Here**.


5


LED Descriptions

Warning! If no battery is installed, then the battery LED is always off.


The following describes the V5 LED indicators.

-  **Battery**
(V5 is running)
 - **LED off:** No battery
 - **LED on:** Battery discharge or battery is charged fully
 - **LED blink slowly:** Battery is charging.
 - **LED blinks quickly:** Battery's capacity is below 10%.


-  **Hard drive**
 - **Red:** The hard drive is being accessed.


-  **Wireless LAN**
 - **Off:** The wireless LAN module is turned off.
 - **On:** The wireless LAN module is turned on.
 - **Blinking:** Data is being transmitted or received.


Note: The wireless WAN module is available only on some V5 models.

-  **Wireless WAN**
 - **Off:** The wireless WAN module is turned off.
 - **On:** The wireless WAN module is turned on.
 - **Blinking:** Data is being transmitted or received.

5 LED Descriptions

5.  **Bluetooth**
 - **Slow blinking:** The *Bluetooth* module is on standby.
 - **Fast blinking:** Data is being transmitted or received.

6.  **Num lock**
 - Lights when the numeric keypad is enabled.


7.  **Caps lock**
 - Lights when Caps Lock mode is enabled. When enabled you can type alphabetic characters without holding the Shift key.







6

Using the Fingerprint Reader

The fingerprint reader allows you to control access to your computer system and applications.

To enroll your finger and use the fingerprint applications, see the bundled Quick Start Guide and Fingerprint Reader Utility Guide or the online help for the fingerprint reader utility.





7


Using Flybook V5 Input Devices

The Flybook V5 incorporates several ways to interact with the operating system and applications. The V5 has a keyboard that emulates a standard keyboard with the addition of Fn hotkeys. The easy to use pointing device enables you to perform the same function as a mouse or touchpad. Buttons are located on both the left and right side of the V5 for easy access. A scroll bar enables you to scroll up and down in web pages or word processing applications. Finally, the stylus emulates a mouse when using the V5 as a tablet computer, and also enables you to write on the screen.

7 Using Flybook V5 Input Devices


Using the Pointing Devices

The pointing device consists of a stick pointer and two sets of dual click-buttons located on the left and right side above the keyboard. The scroll bar emulates a clickable mouse wheel.



Press the stick pointer in the direction that you want the cursor to move. The left buttons emulate the left, center, and right buttons of a standard 3 button mouse. The two right buttons and scroll bar correspond to the two buttons and click wheel of a clickable wheel type mouse.

To customize the pointing device, click **Start | Control Panel** and then double-click the **Mouse** icon to open the pointing device configuration utility. The configuration utility lets you customize settings to your preference. Click **Help** in the pointing device utility for instructions on changing settings.



Using Flybook V5 Input Devices






Using the Stylus

The stylus not only emulates a mouse when the V5 is in tablet mode, it also enables you to interact with the Flybook V5 as you would with paper and pen. You can navigate the OS, write, and draw on the screen.

Calibrating the Stylus for the First Time

Before using the stylus with the Flybook V5, you should first calibrate the display.

For calibrating and using the stylus, please refer to the bundled **Touch Panel Utility Guide** for further information.




7 Using Flybook V5 Input Devices

Using the Keyboard

The V5 keyboard emulates a standard-sized computer keyboard by incorporating function keys, a numeric keypad, and the Fn key.

Using Function (Fn) Keys

Using function keys is a quick way to carry out commands or enable features on your computer. Function keys have a blue icon or have blue text (such as on the **Home** and **PgDn** keys). To use this function, press and hold the **Fn** key (1) and then press a function key (2).



Using Flybook V5 Input Devices **7**

The **Fn** key functions are described as follows.



Note: Pressing some function key combinations (for example, Fn + F8) shows an On Screen Display (OSD) to indicate the function used.



- **Fn + Esc:** Repeatedly pressing the buttons outputs the display signal to one of the following:
 - Connected external display only
 - Both a connected external display and system display
 - System display only
 If no external display is connected, pressing this key combination has no effect.
- **Fn + ~:** Turns the V5 LCD off.
- **Fn + F1:** Decreases the display brightness.
- **Fn + F2:** Increases the display brightness.
- **Fn + F3:** Puts the computer in suspend mode.
- **Fn + F4:** Puts the computer in hibernation mode.
- **Fn + F5:** Mutes/enables the volume.
- **Fn + F6:** Decreases the volume.
- **Fn + F7:** Increases the volume.
- **Fn + F8:** Enables or disables the built-in wireless local area networking (WLAN) feature.


7 Using Flybook V5 Input Devices

- **Fn + F9:** Enables or disables the built-in wireless wide area networking (WWAN) feature.
- **Fn + F10:** Enables or disables the built-in *Bluetooth* feature.
- **Fn + Alt:** Turns on or off the built-in webcam.
- **Fn + Shift:** Turns the GPS function on and off.
- **Fn + ScrLk:** Enables or disables scroll lock. When enabled, press the up or down arrow keys to scroll up or down one line respectively.
- **Fn + PrtSc:** Print screen captures the on-screen image to the clipboard. You can then copy the contents to an image editing program.
- **Fn + SysRq:** Terminal request. This key is rarely used.
- **Fn + Home:** Displays the first page of a document or moves the pointer to the beginning of a line in text.
- **Fn + End:** Displays the last page of a document or move the pointer to the end of a line in text.
- **Fn + PgUp:** Moves text up one screen at a time.
- **Fn + PgDn:** Moves text down one screen at a time.
- **Fn + A:** Enables or disables the automatic light sensor.

Using Flybook V5 Input Devices **7**

Using the Numeric Keypad

The keyboard has an embedded numeric keyboard. When you enable it, the Num Lock LED lights. To enable or disable the numeric keypad, press **Fn + Num Lk**.









The illustration shown here displays the location of the embedded numeric keyboard keys.

Note: Refer to the Windows start here booklet for additional keyboard shortcuts.

Using Windows® and Other Keys

Keys such as the Windows start and application keys, and the **Caps Lock** key function the same as on a standard keyboard in the Windows environment.

-  : Opens the start menu. Use it in combination with other keys to perform Windows shortcuts.
-  : The application key has the same function as the right-mouse button.
- **Caps Lock**: Toggles uppercase on and off.



8


Using Flybook Control Center

The Flybook Control Center lets you quickly enable or disable wireless options and change settings such as volume and display mode. You can also check system health with this utility.

The Control Center is most often used in tablet mode to access frequently used features that are normally accessed with function keys in clamshell mode. Also, some functions available in the Control Center are dedicated for tablet mode use.

8 Using Flybook Control Center

Opening the Control Center


1. Right-click the Flybook icon in the System Tray  and select **Restore**.

The Control Center Opens.



2. Click the left arrow button to open/close the left side pane, and click the right arrow button to open/close the right side pane. The left side pane displays additional function buttons, while the right side pane displays the health information of the system.

Using the Control Center














When the Control Panel displays:





1. Move the pointer over the buttons on the Control Center panel.
2. Click function icons to start (or stop) the functions.





8 Using Flybook Control Center

The following table briefly describes each available function.

Icon	Description
	Turns the volume on and off.
	Turns the automatic light sensor on and off.
	Click  to increase the volume. Click  to decrease the volume.
	Click  to decrease the display brightness. Click  to increase the display brightness.
	Click the buttons to orient the screen in the direction indicated.
	Click to enable or disable the webcam.
	Click to enable or disable the GPS function.

Using Flybook Control Center **8**

Icon	Description
	Click to enable or disable the wireless WAN.
	Click to enable or disable the wireless LAN (WiFi).
	Click to enable or disable the Bluetooth.
	Click to disable all wireless communications devices.



9

Customizing the V5 Display




Note: Alternatively, right-click the desktop and select **Properties** to customize the display.

You can customize the V5 display by using the Windows Display utility.

To open the Display utility:

1. Click **Start | Control Panel**
2. Double-click the Display icon to open the Display Properties window.

Customize the display in the Display Properties window. For more information, refer to the Windows online Help and Support Center.



10

Connecting Devices


This section covers peripheral devices that you can use with the V5.

Connecting Audio Devices

Your computer has a built-in microphone and speaker. You can also connect an external microphone and headset.

Connecting Headphones


Connect speakers or headphones to the headphone jack.



10 Connecting Devices

Connecting a Microphone

Connect a microphone to the microphone jack.



About the Realtek Sound Manager

Note: The built-in speakers and microphone are automatically disabled when you connect external speakers or a microphone.

Your V5 comes with the Realtek Sound Manager, which enables you to configure connected audio devices.


To access the Realtek Sound Manager, click **Start | Control Panel**, and then double-click the **Realtek HD Sound Effect Manager** icon.

Connecting USB Devices

There are two Universal Serial Bus (USB) connectors on the Flybook V5. You can connect USB devices such as printers or flash drives to either connector.

Caution: Be sure the USB icon on the connector is facing downwards as shown in the illustration. Connecting a USB cable incorrectly can damage the connector on the computer.

1. Connect the USB device to one of the USB connectors on the computer.



2. Install drivers for the device as prompted.


10 Connecting Devices

Caution: You can permanently damage a display if it does not support the resolution that your computer is set to. Match the resolution of the V5 to the external display before you attach it to the computer.

Connecting an External Display

You can connect an external monitor, projector or LCD to your computer with a resolution up to 1800 x 1440. Check the user manual of the display to be sure it supports this resolution.

1. Connect the external display to the monitor connector on the computer.




2. Connect the display to an electrical outlet and then turn on the display.
3. Press **Fn + ~** to switch to the external display.

Connecting to a TV

Note: Before outputting the display to a video device, check the device's input signal type and change your computer's output signal type to meet it. The V5 outputs NTSC or PAL video signals. Select the type in BIOS Setup Utility. The default setting is Auto.

You can connect a TV to the Flybook V5 to use as an external monitor.

1. Plug the 3.5 mm TV cable adapter into the TV cable jack at the rear of the Flybook V5.



2. Connect the other end of the TV cable jack to a composite video RCA cable (yellow connector).
3. Press **Fn + ~** to change the V5 output to the television.

10 Connecting Devices


Using an ExpressCard

You can use 34 mm-wide and 54 mm-wide ExpressCards with your Flybook V5.

Caution: Do not install or remove an ExpressCard when the computer is in standby or hibernate mode. Static electricity in your body can damage ExpressCards. To reduce the static electricity in your body, touch a bare metal table or a grounded metal object before installing an ExpressCard.


Installing an ExpressCard

1. Find the notched edge on the card as shown in the following illustration.




34 mm-wide ExpressCard installation

2. Press and release the dummy card inserted in the ExpressCard slot.



The card pops out.


3. Remove the dummy card from the slot.



54 mm-wide ExpressCard installation

10 Connecting Devices

4. Insert the ExpressCard into the slot.



Removing an ExpressCard

1. Click **Safely Remove Hardware** in the taskbar.
2. Select the card and click **Stop**.
3. Push and release the card to eject it.

11

Securing Your V5

Before You Go Online

Connecting your computer to the Internet opens the way to potential threats such as viruses and spyware. To best secure your computer purchase security software (or download it from a secure system), and then install it on your computer before you connect it to the Internet.

To check your computer's security settings click **Start | Control Panel**, and then click **Security Center** in Category View or double-click **Security Center** in Classic View.

Installing a Firewall

A firewall protects your computer by blocking or allowing traffic between your computer and the Internet. Windows has a built-in firewall that helps to protect your computer. For better security, purchase a router that has a built-in firewall. You can also download free firewall software on the Internet.

Installing a Spyware Blocker

Spyware typically retrieves information about your Web-surfing habits. It can be secretly installed on your computer with a free download and can even be installed just by visiting a Web site. Spyware can cause your Web searches to be redirected and pop up annoying adds. Once your computer is infected with spyware, it can be very difficult to remove. The key is to prevent infection in the first place by installing spyware blocker software. Spyware blocking software can be purchased online; and you can even download free spyware blocking programs.

12

Connecting Local Area Networks


Note: For assistance with local network connections, consult your network administrator or see the Windows online Help and Support Center to obtain a solution.

Your computer has an Ethernet connector that you can use to connect to a wired network at home or in the office. If you have a wireless access point, you can also get online using the built-in wireless LAN of your computer.

Connecting a LAN

Wired connections are more secure and more stable than wireless connections. You can connect your computer to the network while it is turned on. Refer to the following to set up a wired connection:

1. Connect an Ethernet cable to the Ethernet connector on the computer.



12 Connecting Local Area Networks

2. Connect the other end of the cable to your router or switch.
It takes a few minutes for your router to assign an IP address to your computer. When your computer is connected, the following message appears over the LAN icon in the System Tray.
3. Double-click the LAN icon to view details for your connection.

Connecting a Wireless LAN (WLAN)

Use your computer's built-in wireless LAN module to access your home or office network. The wireless LAN module is powered by the Intel® PROSet/Wireless utility.

Wireless systems work in infrastructure mode or peer-to-peer mode. In infrastructure mode, wireless devices communicate to a wired LAN via access points. In ad-hoc mode (also known as peer-to-peer mode), wireless devices communicate with each other directly and do not use an access point.

To connect to a wireless network:

1. Press Fn + F8 to enable the wireless LAN module.
2. The Intel(R) PROSet wireless module automatically scans for available networks.
3. Follow the on-screen prompts to access a network. Click **Help** in the Intel® PROSet/Wireless utility for assistance.
4. Click the utility icon in the system tray at any time to open the Intel PROSet Utility.

13

Using the Built-in Modem

The built-in fax/data modem module enables you to connect the V5 to a remote network or the Internet or fax documents.

Making a Dial-up Connection

Before making a dial-up connection, you must install connection components in Windows and create a dialing profile for the connection. More than one profile can be created for different connection purposes.

Creating modem dial-up connection components

To install modem dial-up connection components:

1. Click **Start | Control Panel** and double-click the **Network Connections** icon.
2. Click **Create A New Connection** to open a wizard that will instruct you how to install dial-up connection components and set up a profile.


When a component is created, an associated icon is displayed in the Network Connections window. For more information on installing modem dial-up components, refer to the Windows online Help and Support Center.

13 Using the Built-in Modem

Making a modem dial-up connection

To make a modem dial-up connection:

1. Connect a phone jack to the RJ-11 jack at the rear of the Flybook V5 to use the built-in modem.



2. In the Network Connections panel, double-click the icon of the component you wish to use to make the connection.






Once the connection is established, the icon shows “connected”. Click the icon to open the status window to check or stop the connection, or open its connection properties window and configure this connection component.





Windows supports other modem dial-up connection utilities. If you have other utilities installed, see their guides or on-line helps to learn how to create and make connections.



Sending and Receiving a Fax

The built-in fax/data modem module supports faxing. You can use Windows Fax or other fax applications to send and receive faxes. Windows also provides a fax printer service transferring from printer function of programs. Refer to the Windows online Help and Support Center for further details, or refer to your fax application's online help or user guide.





14

Using the Built-in WWAN Module

Note: The V5 accommodates various 3.5G WWAN modules (HSDPA / UMTS / EDGE / GPRS / GSM) and advanced modules. Please check the model of your V5 to identify the module that is installed.


The optional built-in WWAN module uses cellular carriers for transmission. It enables you to connect your Flybook V5 to the Internet or use the V5 to make phone calls.

Before using the module, you must apply for an access account, and get a SIM card and dialing profile from your wireless WAN service provider. The SIM card acts as an access permission key for your account.



14 Using the Built-in WWAN Module

Installing the SIM Card

1. Remove the battery (refer to [“Battery Installation”](#) on page 13).
2. Locate the SIM card.




3. Push and slide the SIM holder in the direction of the arrow to release the holder.
4. Raise the SIM holder as shown.




Using the Built-in WWAN Module **14**

5. Insert the SIM card making sure it is inserted all the way to the bottom of the slot.



6. Close the SIM card holder and lock it in place.






7. Replace the battery.

Connecting the V5 to a Wireless WAN

1. Press **Fn + F9** to turn on the wireless WAN module, or click the WWAN icon in the Flybook Control Center. Your WWAN utility opens.
2. When the module is turned on, it seeks your service provider's network and registers. If the service provider's network is inaccessible, the module continues to search for other available networks and ask you to select one and register.
3. Double-click the WAN connection status icon in system tray to check the connection status.

Refer to the "Flybook WWAN Utility Guide" booklet or the online help for information on using the utility.



15








Using the Built-in Bluetooth Module

Using the built-in Bluetooth module the computer can communicate with Bluetooth-equipped devices such as computers, cellular phones, printers, faxes, keyboards, and pointing devices. The module also enables you to take advantage of the following versatile Bluetooth services:

- Personal area networking
- Dial-up networking
- Serial port connection
- File transfer
- LAN access
- Synchronization and PIM data exchange
- Printing
- Human interface device (Keyboard, Mouse) connection
- Faxing
- Connecting a headset
- Audio distribution

To enable the Bluetooth module, press **Fn + F10**; a Bluetooth icon appears in the system tray. Double-click the icon to open the main window of the utility.

Read the online help of the Bluetooth utility to see how to use Bluetooth services.












16

Using GPS

The Flybook V5 optionally comes with GPS (Global Positioning System) capability. GPS is a satellite-based radio navigation system. Signals from at least four satellites compute the current latitude, longitude and elevation of a GPS receiver anywhere on earth to within a few meters.

Press **Fn + Shift** to activate the GPS function. The GPS icon appears in the system tray.

For more information on using GPS, consult the online help or user's guide bundled with your GPS application.



17

Using the Built-in Webcam

Note: When a webcam enabled application is open, the webcam LED lights when you turn on the webcam.

Your computer features a built-in webcam that is already set up and ready to use with most of web applications that support video messaging, such as MSN Messenger or Skype.

Enabling the Webcam

To use the webcam:

1. Press **Fn + Alt** to enable the built-in webcam.
2. Open your favorite application and launch the webcam. Refer to the help of the application to learn how to use the webcam.

17 Using the Built-in Webcam


Adjusting the Webcam Orientation

Caution: Be careful to follow the instructions in this section when adjusting the Webcam. Otherwise you may damage it.


The webcam rotates up to 225 degrees, enabling you to adjust it in clamshell and tablet mode for optimum use.

Refer to the following instructions to adjust the webcam orientation.

1. Rotate the webcam for optimum use.



2. Rotate the webcam completely to take video or pictures of a scene (such as a conference) while still being able to use the Flybook V5 for data entry.



18





Managing System Power

The computer controls its power activities through an ACPI power management unit. The unit employs a set of power management schemes to maximize power conservation and optimize system performance. Windows manages all power-saving features and provides a Power Options utility in customizing the computer's power system.

To start the Power Options utility:

1. Click **Start | Control Panel**.
2. Double-click the **Power Options** icon to display the Power Options Properties window.
3. Following the indications to check and change the settings.

Customize your computer's power system in this window. Refer to the Windows online Help and Support Center to see ACPI and Power Options if necessary.



19 Customizing the System BIOS

On the right side of the Setup screen is an area labeled **Item Specific Help**. This area lists navigation key shortcuts and information that is specific for the item that is selected.

Updating the BIOS Firmware

You can download updated BIOS from the manufacturer's Web site and upgrade the BIOS on your computer. New BIOS may provide support for new peripherals, improvements in performance or fixes for known bugs.

To download firmware, please go to <http://www.dialogue.com.tw>.

A

Troubleshooting

In each problem-specific section, try the steps in the order suggested. This may help you to solve the problem more quickly.

Try to pin point the problem and thus avoid replacing non-defective parts.

Keep a record of the steps you take when troubleshooting: The information may be useful when calling for technical support or for passing on to service personnel.

Identifying Problems

Follow the steps below to identify your problems:

1. Turn off the computer.
2. Disconnect any peripheral devices such as an external mouse or printer.
3. Make sure that the AC adapter is properly connected to your computer and the power source is good. (Use some other electrical device to confirm that the electrical outlet is working.)
4. Leave the computer off for approximately 10 seconds, and then switch it on again. The computer should enter the boot sequence and start normally.
5. If the computer does not start normally, look for a screen message or other clue on the malfunction.

If failure is detected in an area other than the mainboard, an error message is displayed on the screen and testing is stopped.

If your system does not successfully start, but displays a blank screen, emits a series of beeps, or displays an error code, consult your dealer.

General Hardware Problems

A few common hardware problems and suggested solutions are presented below:

The display screen is dark

1. Adjust the screen brightness.
2. Make sure that the computer is not in suspend mode.

An incorrect date and time are displayed.

Correct the date and time using the DOS DATE and TIME commands or the options in the Setup Utility. (You can also set the date and time in Windows by double clicking the clock on the task bar or in the control panel.) If the date and time become incorrect after a short time, your CMOS battery may be depleted. Contact your dealer to change the battery.

The computer does not start or boot-up

1. If the power indicator is not on, the computer is without power. Make sure you have properly attached the AC adapter and power cord, or have installed a charged battery.
2. If the computer is running on battery power, ensure that the battery charge is not low. If the battery appears to be charged, it may be faulty.

3. If the computer is using the AC adapter, ensure that the AC outlet, airplane seat jack, or car cigarette lighter are working. If the AC outlet power is working, the AC adapter may be faulty.

Hard drive or external boot-up device is inaccessible

1. If the hard disk indicator is lit, BIOS may be incorrectly set. Revise the BIOS settings for the Primary Master.
2. Security may be set to prevent starting the operating system.
3. If you choose to boot up your system from an external device through a USB port, make sure it is on and bootable media is inserted.

The screen is blank or the display is abnormal

1. The computer may be set to an external display device only. Press **Fn + F1** to switch to the V5 display.
2. The power management system may automatically blank the screen to save power, and is in video time-out, standby mode, or hibernation mode. Press any key, move the pointer, or push the power button to turn on the display.
3. The angle of the display and the brightness level is inadequate for the ambient lighting. Adjust the display angle and press **Fn + F2** or **Fn + F3** to adjust the brightness level.
4. The LCD screen has a default resolution of 1280 x 768 (WXGA). If you set the resolution lower than this, the screen expands to fill the display. When the system can not expand its display to full screen on the LCD screen or on an external display device, you can right click on Windows desktop and select **Properties** to open the **Display Properties** window. Then click the **Settings** tab and set the resolution to an appropriate value.

A Troubleshooting

No audio output

1. The audio system is closed or the volume of audio system is too low. Use hot keys or Flybook Control Center to open the audio system and adjust the volume.
2. The audio output is disabled or too low for the audio application. Open the audio output and adjust the volume.
3. When plugging an earphone or external speaker into the earphone/line-out jack, the built-in speakers are disabled automatically. If you can not hear sound from the built-in speakers, ensure that nothing is plugged into the jack.

The keyboard, pointing device or connected mouse does not work properly

1. The system may have entered Suspend to RAM mode. Push the power button to resume the system.
2. An application may have locked out your input device. Restart your system.
3. If the keyboard or mouse does not respond on the USB port, ensure that the devices are installed properly and that drivers are installed.

Cannot connect to a wireless LAN

1. An incorrect network name (SSID) or network key may be used. Make sure you have set the network name (SSID) and key to the same values as the access point (infrastructure connection) or the computers to be connected (Ad Hoc connection) have.
2. The computer may be too far from other communication devices. Retry the connection after moving your computer closer to the computers to be connected with (Ad Hoc connection) or to the access point (infrastructure

connection). Also, check the wave condition in the Wireless Network Connection Status window.





3. Check if the wireless LAN module is turned on. Verify that Disable Radio is not checked in the Network setting window.
4. Make sure you have access rights or network authentication to the network you want to connect to.
5. Try changing channels to avoid active channel duplication.
6. Check the setting of the protocol, work group, shared setting, and IP address.

Cannot charge battery or losing power quickly

1. Verify that the battery is properly installed and it is not too hot or too cold.
2. Calibrate the battery.
3. The installed battery may be faulty. Replace it with a new one.

Having the V5 Serviced

If you are unable to solve the problem, you should have the computer serviced. Pack the computer in the original carton. Include a description of the problem and a checklist of the steps you took when trying to fix the problem. The information may be useful to the service personnel. Return the computer to the place you purchased it.



B

Specifications

Processor	Intel® Centrino® Duo ULV
Chipset	Mobile Intel® 945 GM Express Chipset
Main Memory	DDR2 SO-DIMM, up to 4GB
BIOS and Flash	Phoenix® TC BIOS
Operating System	Genuine Microsoft® Windows® Vista / XP
Wireless WAN (optional)	3.5G (HSDPA / UMTS / EDGE / GPRS / GSM) or advanced with antenna built-in
Wireless LAN	802.11a/b/g (Intel® 3945 supported) with antenna built-in
Wireless PAN	Bluetooth® V2.0 with antenna built-in
GPS (optional)	GPS receiver with antenna built-in
LAN	10/100/1000 Mbps Ethernet
Fax / Modem	Azalia Compliant and V.92 / K56flex support
Swivel Hinge	For both Clam-shell and Tablet mode operation
Display	8.9", 16:9 wide-view Color LTPS TFT LCD with 1024 x 600 (WSVGA) high resolutions(32-bit colors)
External VGA Display	Up to 2048 x 1536 resolutions (highest to 32-bit colors)
External TV Display	NTSC / PAL support
Video Camera	1.3 mega pixel web camera, 180°
Audio	Array Microphone / Stereo Speaker built-in
Authentication	Finger-Print device and recognition built-in

B Specifications

Hard Drive	1.8" Ultra Slim Hard Disk, 40/60/80 GB (4200 rpm)
Input devices	Touch Panel; Landscape and Portrait dual mode Pointing device with 2 sets of Mouse buttons and a clickable scroll bar 80 Key standard keyboard (Multiple languages support) with hot keys
Interface	USB 2.0 port x 2 RJ-45 LAN jack x 1 RJ-11 Modem jack x 1 Earphone jack x 1 Microphone jack x 1 54mm-wide PCI Express Card slot x 1 D-sub 15 pin VGA port x1 (for external monitor) TV-out jack x 1
Battery	Swappable Li-Ion rechargeable battery (6 x 1800mAH)
Dimensions	Dimensions: 235 x 165 x 29.5 mm Weight around 1270g (when fully equipped)
Color Selection	Gold / Pink / Black / Silver


Electrical specifications

DC-In power supply (Through DC-IN Power Jack)

- Input Rating: 15-19VDC, 2.64-3.34A, 50W.
- Maximum Operating Temperature (Ambient): 38 degrees C

AC adapter




- Model No: Delta ADP-50HH Rev. A.
- Input Rating: 100-240VAC, 50-60Hz, 1.5A.
- Output Rating: 19VDC, 2.64A, Class II, Marked LPS.




Specifications **B**




Battery

- Battery Pack: 6 cell 3S2P 103450 Li-Ion rechargeable battery pack.
- Charging: Direct DC charging.



75





Index

A

AC adapter	
connecting	16
connector, location	5
access account	53
air vent, location	8
application, key	27
audio devices	
connecting	37
headphones, connecting	37
microphone, connecting	38

B

battery	
charging	15
charging time	15
installing	14
LED	17
locks	13
removing	15
BIOS	
accessing	65
description	65
type	73
updating	66

Bluetooth	
enabling	26, 57
LED	18
using	57
brightness	
decreasing	25
increasing	25

C

calibrating, stylus	23
caps lock, LED	18
charging the battery	15
chipset	73
clamshell mode	9
cleaning the Flybook V5	viii
connecting	
AC adapter	16
audio devices	37
external display	40
microphone	38
USB devices	39
Control Center	
functions	32
opening	30

Index

D

display

- clamshell mode 9
- connecting external 40
- resolution 40
- tablet mode 10

E

Ethernet

- connecting LAN 47
- connector, location 7

ExpressCard

- installing 42
- removing 44
- slot, location 8
- using 42

F

faxing 51

fingerprint reader

- enrolling fingerprint 19
- location 4
- using, 19

fingerprint, enrolling 19

firewall, installing 45

Flybook control center

- using 30, 31

Flybook V5

- cleaningviii

do's and don'ts v

introduction 1

powering on 16

tour 3

fn key

- function description 25
- using 24

front-left view 3

G

GPS

- turning on and off 26
- using 59

H

hard drive

- capacity 74
- LED 17

headphones

- connecting 37
- jack, location 7

hibernation 69

mode, enabling 25

I

installing

- battery 14
- ExpressCard 42

firewall 45
 spyware blocker 46

turning on and off 26

K

keyboard
 using 24
 keys
 application key 27
 caps lock 27
 fn 24
 numeric keypad, using 27
 start key 27
 Windows keys 27

L

LAN
 connecting 47
 wireless 48
 LEDs
 battery 17
 Bluetooth 18
 caps lock 18
 description 17
 hard drive 17
 location 4
 num lock 18
 wireless LAN 17
 wireless WAN 17
 light sensor
 location 6

M

memory 73
 microphone
 built-in, location 5
 connecting 38
 jack, location 8
 modem
 creating a dial-up connection . 50
 creating dial-up components .. 49
 faxing 51
 jack, location 7
 monitor, connector location 7

N

num lock
 enabling 27
 LED 18
 numeric keypad
 using 27

O

operating system 73
 OS see operating system

Index

P

pointing device
 buttons, location 4, 5
 customizing 22
 location 4
 track stick 4
 using 22
 power button, location 5
 power management
 power options utility 63
 power options utility
 starting 63
 powering on 16
 processor 73

R

Realtek Sound Manager 38
 rear view 7
 RF kill switch, location 4

S

scroll bar
 location 4
 security
 firewall, installing 45
 spyware blocker, installing 46
 service
 contacting vii
 returning the V5 for 71

SIM card 53
 installing 54
 speakers, location 5
 specifications 73
 spyware blocker, installing 46
 strap slot, location 8
 stylus
 calibrating 23
 using 23
 suspend mode 25, 68

T


tablet mode 10
 troubleshooting 67–71
 general problems 68
 identifying problems 67
 TV
 connecting 41
 connector, location 7

U

updating BIOS 66
 USB device
 connecting 39
 using fingerprint reader, 19

V






view






front-left 3
rear 7
volume
decreasing 25
increasing 25
muting 25

W

webcam
adjusting orientation 62
enabling 61
location 5
turning on and off 26
using, 61
Windows, key 27
wireless LAN
connecting 48
enabling and disabling 25
LED 17
wireless WAN
connecting 55
enabling and disabling 26
LED 17
WLAN see wireless LAN
WWAN dial-up connection utility .. 55
WWAN see wireless WAN





This publication, including all photographs, illustrations and software, is protected under international copyright laws, with all rights reserved. Neither this manual, nor any of the material contained herein, may be reproduced without written consent of the manufacturer.

© Copyright 2007 Dialogue Technology Corporation

