

connecting the future



a strong range of flexible solutions for CATV network, hotels and multi-dwelling units













Reliability is our business. It's what we stand for.

For nearly 70 years, TRIAX has strived to be your preferred partner for all your connectivity needs. We're proud to provide reliable solutions for the present, while connecting our customers to the future.

At the forefront of technological trends and developments, we're with you each step of the way, from installing home connections and business critical hospitality solutions, to realising complex, large scale integrations.

Ready for any job at hand, our products are available individually or as part of tailor-made

solutions. From aerials and dishes, to headends, outlets, cables and beyond – we make connectivity easy, ensuring you live up to your own customer promises.

Rest assured that at TRIAX, reliability and innovation run through the core of everything we do, from product development to our friendly, efficient service and support.

So enjoy browsing through this catalogue for an overview of our full product range. And of course, we're always just a phone call away for more inspiration towards your next solution.

Contact TRIAX

To place an order or consult one of our experts, contact us via:


Phone:	+45 76 82 22 00
e-mail:	triax@triax.com

Or pay us a visit online at www.triax.com, where you'll find a wealth of further material about our products and solutions.

TRIAX® Headend Solutions

find the right headend for your needs

Content	Page
Headends	
■ TDX	6-17
TDH 800	18-25
Conditional Access Systems	
CAS Hospitality	26
CAS Operator	27
Modulators	28-29



TRIAX® headends

overview of our headend system



TDX BLACK EDITION



...a strong headend for medium sized CATV networks, town districts, CATV clusters, etc. The ultimate flexible hospitality solution including DRM interface and middleware support via IPTV signals

- Multi-unit (48 frontends and 72 output channels)
- Wide range of input and output technologies
- Simultaneous output of QAM/COFDM, PAL and IP
- Multiplexing
- Remote management and monitoring
- Local Service and hotel info channel insertion
 - PID Management to adapt PIDs if required
 - to secure Service changes without retuning of the television in each room
 - One-stop solution (TDX in combination with the TRIAX CAS solution)
- Encryption and re-scrambling in one unit with no insecure interfaces to the decrypted content
- Provide scrambled services on differed distribution networks and technologies. Simultaneously distribution of QAM, COFDM and/or IP.
- IP-out for IPTV and middleware solutions

TDH 800



...a modular solution for hotels, multi-dwelling units, and as an add-on programme solution

- Wide range of input and output technologies
- Simultaneous output of QAM/COFDM and PAL
- Multiplexing
- Remote management and monitoring
- PID Management: to secure service changes without retuning of the television in each room
- Local service and hotel info channel insertion

TDX Black Edition

technology that turns everything on its head

TDX headend – quite simply a revolution

Forget everything you know about headends: with TRIAX TDX you move into a completely new world. TRIAX's revolutionary IP Pool technology simplifies the setting up and management of headends, making the input and output modules

Energy friendly – long-term reliability

- 16 tuners, fully loaded 280W power consumption
- Intelligent cooling system with integrated fans increases the life of the equipment and allows installation in 19" cabinets

Easier service handling

- HOT SWAP service
- Fewer modules allows easy spare part handling
- Log file on all TDX activity
- Remote access to the TDX for the installer and/or TRIAX support

Easy setup and configuration

- HTML based user interface means no special software for managing the system
- Mux bandwidth monitor to ensure that the mux is not overloaded
- The respective four adjacent output channels can be freely selected across the full frequency range
- LED to indicate operation and errors on each module
- Intuitive and easy, step-by-step configuration

mutually independent. All input signals, regardless of whether they are received via satellite, terrestrial, cable, audio/video or via the Internet, can be flexibly and independently distributed from a "pool" to each and every output module. Each of these input signals can be converted to any output signal: PAL, QAM, COFDM or IP, and because the input signals are not fixed to any particular outputs, they can be assigned to several output modules.

Better and stronger performance

Up to three headends can be combined into a multi unit system Up to 72 PAL, QAM or COFDM channels



A true IP headend

- Muxing technology
- IP in to any output
- IP out from any input
- Future proof: full compatibility with CAS systems, middleware, PMS, VOD services, EPG server, etc.

Easy installation

- Input modules are independent of output modules, resulting in fewer modules in total
- Faster installation
- DiSEqC 1.1 functionality
- The housing is designed to accommodate up to 16 input and 6 quad output modules. The output modules provide the possibility to support 12 CAM modules
- Can easily be installed on a wall or a 19" cabinet
- All inputs and outputs as well as all modules and cables can be accessed and operated easily from the front
- The 22 modules are numbered so their respective allocations are always immediately clear
- Cabinet lock system
- Cable management on top, left and right



TRIAX® TDX cabinet

main unit for TDX range of modules





User-friendly technology

- Fully configurable: all implementation variants are possible with significantly fewer modules than a standard headend, thereby reducing costs for acquisition, service and warehousing
- Browser-based (HTML5) user interface configuration.
 Infinite variety of programmes thanks to revolution-
- ary IP-pool technology, that makes TDX Black Edition uniquely flexible, efficient and economical

Futureproof

IPTV offers video on demand, time-shifted television, many additional services for hoteliers, trade shows and much more

- No re-programming of the TV sets when a channel changes, thanks to PID management
- Energy-saving and durable

Perfect service for installers

- New modules are automatically recognised and configured
- No downtime for TV customers, as modules can be replaced during operation (hot swap)
- Supplied ready to fit the desired configuration
- Halved installation times due to easy programming
- Remote access for service and support

TDX Black Edition Main Unit



Art. No. 492091 EAN Number 5702664920919



TDX Black Edition

technology that turns everything on its head

Easy to install. Easy to use.

The configuration XML file from the headend system can be stored anywhere as a backup, and can be installed rapidly on a new installation.

In close collaboration with installers, TRIAX has optimised system handling: installation and commissioning is very easy, and operating the system is straightforward for both users as well as service staff.





Type: Art. no.	TDX Black Edition Main Unit 492091
CHARACTERISTICS	492091
Max. LNB control	4 x 305mA
Output level max. @ 60 dB IMD - 24 combined channels	103dBµV
Test point	-20dB
FREQUENCY	
Frequency range (RF OUT)	47 - 862MHz
RETURN LOSS	
Return loss (RF OUT)	> 14 dB at 47 MHz (-1,5 dB/octave; min. 10 dB)dB
ELECTRICAL	
Impedance	75Ω
OPERATIONAL	
Humidity - operating	20 80%
Humidity - storage	10 90%
AC Supply voltage	190 - 260 (50/60) HzVAC
Power Consumption (typ.)	280 (min. 20)W
Temperature - operating	-10 +50°C -20 +70°C
Temperature - storage CONNECTORS	-20 +70 C
External RF OUT	F-connector
External test point	F-connector
PC interface	RJ 45
SFP cage	SFP Module (Cat5/Opto)
MECHANICAL	
Dimensions product (H x D x W) (HE)	290 x 240 x 440 mm / 6.5
Weight (kg)	12.0 kg
Packing QTY	1
Remarks	SNMP version : V1 & V2c

TRIAX® TDX input modules

DVB-C - DVB-S/S2 - DVB-T/T2 - HDMI & AV frontend encoder modules





DVB-S/S2

An input module for the reception of digital satellite signals in a TDX headend system.

The module can receive a complete transponder and all services on the chosen frequency can be transferred to the TDX pool. The DVB-S/S2 frontend module includes an IF tuner and a QPSK/8PSK demodulator with serial transport stream input to the TDX headend system.

DVB-T/T2

A frontend input module for the reception of both T and T2 digital terrestrial signals.


The module can receive a complete terrestrial mux and send all services in the mux to the TDX pool.

DVB-C

An input QAM demodulator module for the reception of a complete cable mux, sending all services in the mux to the TDX pool. The DVB-C frontend module includes a tuner, with integrated gain control and channel filtering, and a QAM demodulator with serial transport stream input to the TDX system.



TDX Frontend - DVB-S/S2 [QPSK/8PSK]





TDX Frontend - DVB-T/T2 [COFDM]

Art. No. 492023 EAN Number 5702664920230

x 1



TDX Frontend - HDMI [Encoder module]

Art. No. 492030 EAN Number 5702664920308





TDX Frontend - DVB-C [QAM] Art. No. 492024 EAN Number 5702664920247



TDX Frontend - AV [Encoder module]

Art. No. 492080 EAN Number 5702664920803



TRIAX[®] TDX input modules DVB-C - DVB-S/S2 - DVB-T/T2 - HDMI & AV frontend encoder modules

HDMI & AV


The AV encoder module converts analogue video (CVBS) and the HDMI encoder module converts digital signals from a set top box, a DVD player, a camera or other sources, into a MPEG2 or MPEG4 data stream.

This data stream is then available in the TDX pool and can be sent out on all TDX output modules.

A 15 pol Sub-D or HDMI cable can be used to connect the source to the AV or HDMI module is also available.

Type: Art. no.	TDX Frontend DVB-S/S2 [QPSK/8PSK] 492020	TDX Frontend DVB-T/T2 [COFDM] 492023	TDX Frontend DVB-C [QAM] 492024	TDX Frontend HDMI [Encoder modul] 492030	TDX Frontend AV [Encoder module] 492080
CHARACTERISTICS Audio embedded				AAC, 48 kHz/ MPEG-2(L1)	AAC, 48 kHz/ MPEG-2(L1), Stereo
Code rates DVB-T Code rates DVB-T2 Constellations DVB-T		1/2, 2/3, 3/4, 5/6, 7/8 1/2, 2/3, 3/4, 5/6 QPSK, 16QAM, 640AM		WFLG-Z(LT)	MFLG-2(LT), Steleo
Constellations DVB-T2		QPSK, 16QAM, 64QAM, 256QAM			
Demodulator		QPSK, 16QAM,	16 QAM, 64 QAM, 128 QAM, 256 QAM		
Demodulator Symbolrate Demodulator Type DiSEqC level FFT mode DVB-T FFT mode DVB-T2 Guard Interval DVB-T Guard interval DVB-T2		COFDM 2K, 8K 1K, 2K, 8K, 16K, 32K 1/4, 1/8, 1/16, 1/32 1/4, 1/8, 1/16, 1/32,			
Input Aspect Ratio Input audio level Input level Input Video S/N Ratio	5575dBµV	1/128 4575dBµV	4575dBµV		4:3 or 16:9 2.4Vpp > 52dB
Input video standards				480i30; 480p30 576i25; 576p50; 720p50/60; 1080p/i25/30	PAL, Secam
LNB LO/HI programmable LNB V/H programmable FREQUENCY	0/22kHz 01318/300V/mA				
Input Audio Freq. Linearity Input frequency range	950-2150MHz	177.5-226.5/474 - 858MHz	114 - 858MHz		± 0.75dB
GAIN Input noise figure RETURN LOSS		< 7.0dB	< 7.0dB		
Input return loss ELECTRICAL	>10dB	> 6.0dB	> 7.0dB		> 26dB
Harmonic Distortion Max. Impedance Input Audio Impedance Physical Interface OPERATIONAL	75Ω	75Ω	75Ω	75Ω	< 1% 75Ω 10 ± 1kΩ CVBS
DC Operating voltage DC Current cons.(typ.) Humidity - operating Temperature - operating CONNECTORS	12 ± 1VDC OFF 150/ON 450mA 2080% -10+50°C	12 ± 1VDC 275mA 2080% -10+50°C	12 ± 1VDC 120mA 2080% -10+50°C	12 ± 1VDC < 320mA 2080% -10+50°C	12 ± 1VDC mA 2080% -10+50°C
Connector Type Connector IN Number of inputs MECHANICAL	F-female 1	F-female 1	F-female 1	HDMI female (A) 1	15pol Sub-D 1 x AV-signal
Dimensions (H x D x W) Packing QTY	29 x 132 x 50mm 1	29 x 132 x 50mm 1	29 x 132 x 50mm 1	29 x 126 x 53mm 1	29 x 126 x 53mm 1

quad QAM backend module DVB-C in FTA or with 2 x CI slot






TDX quad QAM

These backend output modules that enable you to create up to 4 muxes of services / TV programmes available from the TDX pool. The services are distributed in a QAM data stream and can be combined so that the bandwidth of each output mux is optimised. The mux bandwidth monitor function in the TDX service tool ensures that you don't overload the bandwidth and cause problems with the transmission.

TDX quad COFDM

These backend output modules enable you to create up to 4 muxes of services / TV programmes available from the TDX pool. The services are distributed

in a COFDM data stream and can be combined so that the bandwidth of each output mux is optimised. The mux bandwidth monitor function in the TDX service tool ensure that you don't overload the bandwidth and cause problems with the transmission.



quad COFDM backend module DVB-T in FTA or with 2 x CI

Multi-Unit for more power

- Up to three TDX headends can be combined as one system.
- Up to 72 PAL, QAM or COFDM channels are possible (around 280 HD programmes or 570 SD programmes).
- High output level at 103 dBµV for interference free reception.





Art. no. 492055 492056 492060 492061 CHARACTERISTICS 2K 2K Deinterleaver 1=12 1=12 FEC block code RS 204, 188 RS 204, 188 Guard Interval 1/32, 1/16, 1/8, 1/4 1/32, 1/16, 1/8, 1/4 MER ≥ 41.0 (typ. 42)dB ≥ 41.0 (typ. 42)dB ≥ 36 (typ. 38)dB ≥ 36 (typ. 38)dB Output level adjustment +317dB +317dB +317dB +317dB Output Level System 100dBµV 100dBµV 100dBµV 100dBµV Output QAM Modes 16 QAM, 32 QAM, 46 QAM, 128 QAM, 64 QAM, 64 QAM, 64 QAM, 256 QAM QPSK QPSK Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% Spurious Signals > 60dB > 60dB > 60dB Spurious Signals > 60dB > 60dB > 60dB > 60dB 205.F a 58MHz 7, 8, 8.5MHz 7, 8, 8.5MHz 7,
Carrier supported2K2KDeinterleaverI=12I=12FEC block codeRS 204, 188RS 204, 188Guard Interval1/32, 1/16, 1/8, 1/41/32, 1/16, 1/8, 1/4MER≥ 41.0 (typ. 42)dB≥ 41.0 (typ. 42)dB≥ 36 (typ. 38)dBOutput level adjustment+317dB+317dB+317dBOutput Level System100dBµV100dBµV100dBµVOutput Level System100dBµV100dBµV100dBµVOutput Level System100dBµV100dBµV100dBµVOutput Level System16 QAM, 32 QAM,16 QAM, 32 QAM,16 QAM,0utput Level System100dBµV100dBµV100dBµVOutput Symbol rate3.15 - 7.2Mbit/s3.15 - 7.2Mbit/sMbit/sReed Solomon decoder204, 188, t=8204, 188, t=8204 byte mode204 byte modeReed Solomon decoder204, 188, t=8204, 188, t=8204 byte mode204 byte modeSpurious Signals> 60dB> 60dB> 60dB> 60dBFREQUENCYFrequency step250kHz250kHz250kHzBandwidth7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHzFrequency step250kHz250kHz250kHz250kHzOutput frequency range50.5 - 858MHz50.5 - 858MHz50.5 - 858MHzOutput Return Loss> 10dB> 10dB> 10dB
Deinterleaver I =12 I =12 FEC block code RS 204, 188 RS 204, 188 RS 204, 188 Guard Interval 1/32, 1/16, 1/8, 1/4 1/32, 1/16, 1/8, 1/4 MER ≥ 41.0 (typ. 42)dB ≥ 41.0 (typ. 42)dB ≥ 36 (typ. 38)dB ≥ 36 (typ. 38)dB Output level adjustment +317dB +317dB +317dB +317dB Output Level System 100dBµV 100dBµV 100dBµV 100dBµV Output QAM Modes 16 QAM, 32 QAM, 16 QAM, 22 QAM, 64 QAM, 16 QAM, 64 QAM, 64 QAM, 256 QAM QPSK QPSK Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% Spurious Signals > 60dB > 60dB > 60dB FREQUENCY 7, 8, 8.5MHz 7, 8, 8.5MHz 7, 8, 8.5MHz 7, 8, 8.5MHz Channel Raster 7, 8, 8.5MHz 7, 8, 8.5MHz 7, 8, 8.5MHz 7, 8, 8.5MHz 250.5 - 858MHz 250.5 - 858MHz
FEC block code RS 204, 188 RS 204, 188 Guard Interval 1/32, 1/16, 1/8, 1/4 1/32, 1/16, 1/8, 1/4 MER ≥ 41.0 (typ. 42)dB ≥ 41.0 (typ. 42)dB ≥ 36 (typ. 38)dB ≥ 36 (typ. 38)dB Output level adjustment +317dB +317dB +317dB +317dB Output Level System 100dBµV 100dBµV 100dBµV 100dBµV Output QAM Modes 16 QAM, 32 QAM, 64 QAM, 32 QAM, 64 QAM, 64 QAM, 64 QAM, 64 QAM, 256 QAM QPSK QPSK Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% 15% Spurious Signals > 60dB > 60dB > 60dB > 60dB > 60dB SoldB SoldB > 60dB SoldB > 60dB SoldB > 60dB SoldB SoldB <t< td=""></t<>
I/32, 1/16, 1/8, 1/41/32, 1/16, 1/8, 1/4MER≥ 41.0 (typ. 42)dB≥ 41.0 (typ. 42)dB≥ 36 (typ. 38)dB≥ 36 (typ. 38)dBOutput level adjustment+317dB+317dB+317dB+317dBOutput Level System100dBµV100dBµV100dBµV100dBµVOutput QAM Modes16 QAM, 32 QAM, 64 QAM, 128 QAM, 256 QAM16 QAM, 32 QAM, 64 QAM, 128 QAM, 256 QAM16 QAM, 64 QAM, QPSK64 QAM, QPSKOutput symbol rate3.15 - 7.2Mbit/s3.15 - 7.2Mbit/sMbit/sReed Solomon decoder204, 188, t=8204, 188, t=8204 byte modeRoll-Off Factor15%15%Spurious Signals> 60dBFREQUENCY7, 8MHz7, 8MHz6, 7, 8MHzBandwidth7, 8MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHzChannel Raster7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHzOutput frequency step250kHz250kHz250kHz250kHzOutput frequency range50.5 - 858MHz50.5 - 858MHz50.5 - 858MHzRETURN LOSS> 10dB> 10dB> 10dB> 10dB
MER≥ 41.0 (typ. 42)dB≥ 41.0 (typ. 42)dB≥ 36 (typ. 38)dB≥ 36 (typ. 38)dBOutput level adjustment+317dB+317dB+317dB+317dBOutput Level System100dBµV100dBµV100dBµV100dBµVOutput QAM Modes16 QAM, 32 QAM, 64 QAM, 128 QAM, 256 QAM16 QAM, 32 QAM, 64 QAM, 128 QAM, 256 QAM16 QAM, 64 QAM, QPSK64 QAM, QPSKOutput symbol rate3.15 - 7.2Mbit/s3.15 - 7.2Mbit/sMbit/sMbit/sReed Solomon decoder204, 188, t=8204, 188, t=8204 byte mode204 byte modeRoll-Off Factor15%15%Spurious Signals> 60dB> 60dB> 60dBFREQUENCY7, 8MHz7, 8MHz7, 8MHz7, 8, 8.5MHz7, 8, 8.5MHzBandwidth7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHzChannel Raster7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz250kHz250kHz250kHzQutput frequency range50.5 - 858MHz50.5 - 858MHz50.5 - 858MHz50.5 - 858MHz50.5 - 858MHzRETURN LOSS> 10dB> 10dB> 10dB> 10dB> 10dB
Output level adjustment +317dB
Output Level System 100dBµV 100dBµV 100dBµV 100dBµV Output QAM Modes 16 QAM, 32 QAM, 64 QAM, 32 QAM, 64 QAM, 16 QAM, 64 QAM, 64 QAM, 256 QAM 64 QAM, 128 QAM, 64 QAM, 64 QAM, 64 QAM, 64 QAM, 256 QAM QPSK QPSK Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% Spurious Signals > 60dB > 60dB > 60dB FREQUENCY 5 7, 8MHz 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz Channel Raster 7, 8, 8.5MHz Frequency step 250kHz 250kHz 250kHz 250kHz 250kHz Output frequency range 50.5 - 858MHz Output Return Loss > 10dB > 10dB > 10dB > 10dB > 10dB
Output QAM Modes 16 QAM, 32 QAM, 64 QAM, 128 QAM, 256 QAM 16 QAM, 32 QAM, 64 QAM, 128 QAM, 256 QAM 16 QAM, 64 QAM, QPSK 16 QAM, 64 QAM, QPSK Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% Spurious Signals > 60dB > 60dB > 60dB FREQUENCY 7, 8MHz 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz Channel Raster 7, 8, 8.5MHz Output frequency range 50.5 - 858MHz Output Return Loss > 10dB > 10dB > 10dB > 10dB > 10dB
$\begin{tabular}{ c c c c c c c } \hline 64 QAM, 128 QAM, & 64 QAM, 128 QAM, & 64 QAM, & 64 QAM, \\ 256 QAM & 256 QAM & QPSK & QPSK \\ \hline 0utput symbol rate & 3.15 - 7.2Mbit/s & 3.15 - 7.2Mbit/s & Mbit/s & Mbit/s \\ \hline Reed Solomon decoder & 204, 188, t=8 & 204, 188, t=8 & 204 byte mode & 204 byte mode \\ \hline Roll-Off Factor & 15\% & 15\% & \\ \hline Spurious Signals & > 60dB \\ \hline FREQUENCY & & & & \\ \hline Bandwidth & 7, 8MHz & 7, 8MHz & 6, 7, 8MHz & 6, 7, 8MHz & \\ \hline Channel Raster & 7, 8, 8.5MHz & 7, 8, 8.5MHz & 7, 8, 8.5MHz & 7, 8, 8.5MHz & \\ \hline Frequency step & 250kHz & 250kHz & 250kHz & 250kHz & 250kHz & \\ \hline Output frequency range & 50.5 - 858MHz & 50.5 - 858MHz & 50.5 - 858MHz & \\ \hline RETURN LOSS & > 10dB \\ \hline \end{tabular}$
256 QAM 256 QAM QPSK QPSK Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% 204 byte mode 204 byte mode Spurious Signals > 60dB > 60dB > 60dB > 60dB > 60dB FREQUENCY 7, 8MHz 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz Channel Raster 7, 8, 8.5MHz Frequency step 250kHz 250kHz 250kHz 250kHz 250kHz Output frequency range 50.5 - 858MHz Output Return Loss > 10dB > 10dB > 10dB > 10dB > 10dB
Output symbol rate 3.15 - 7.2Mbit/s 3.15 - 7.2Mbit/s Mbit/s Mbit/s Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15% 204 byte mode 204 byte mode Spurious Signals > 60dB > 60dB > 60dB > 60dB > 60dB FREQUENCY 7, 8MHz 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz Channel Raster 7, 8, 8.5MHz Frequency step 250kHz 250kHz 250kHz 250kHz 250kHz Output frequency range 50.5 - 858MHz RETURN LOSS > 10dB > 10dB > 10dB > 10dB
Reed Solomon decoder 204, 188, t=8 204, 188, t=8 204 byte mode 204 byte mode Roll-Off Factor 15% 15%
Roll-Off Factor 15% 15% Spurious Signals > 60dB > 60dB > 60dB FREQUENCY
Spurious Signals FREQUENCY> 60dB> 60dB> 60dBBandwidth7, 8MHz7, 8MHz6, 7, 8MHz6, 7, 8MHzChannel Raster7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHz7, 8, 8.5MHzFrequency step250kHz250kHz250kHz250kHzOutput frequency range50.5 - 858MHz50.5 - 858MHz50.5 - 858MHzRETURN LOSS0utput Return Loss> 10dB> 10dB> 10dB
FREQUENCY Bandwidth 7, 8MHz 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz Channel Raster 7, 8, 8.5MHz 7, 8, 8.5MHz 7, 8, 8.5MHz 7, 8, 8.5MHz Frequency step 250kHz 250kHz 250kHz 250kHz Output frequency range 50.5 - 858MHz 50.5 - 858MHz 50.5 - 858MHz 50.5 - 858MHz RETURN LOSS 0utput Return Loss > 10dB > 10dB > 10dB > 10dB
Bandwidth 7, 8MHz 7, 8MHz 6, 7, 8MHz 6, 7, 8MHz Channel Raster 7, 8, 8.5MHz Frequency step 250kHz 250kHz 250kHz 250kHz 250kHz Output frequency range 50.5 - 858MHz 50.5 - 858MHz 50.5 - 858MHz 50.5 - 858MHz RETURN LOSS Vutput Return Loss > 10dB > 10dB > 10dB
Channel Raster 7, 8, 8.5MHz 250kHz 250.5 - 858MHz 50.5 - 858MHz 50
Frequency step250kHz250kHz250kHz250kHzOutput frequency range50.5 - 858MHz50.5 - 858MHz50.5 - 858MHz50.5 - 858MHzRETURN LOSSOutput Return Loss> 10dB> 10dB> 10dB
Output frequency range 50.5 - 858MHz 50.5 - 858MHz 50.5 - 858MHz 50.5 - 858MHz RETURN LOSS Output Return Loss > 10dB > 10dB > 10dB > 10dB
RETURN LOSS Output Return Loss > 10dB > 10dB > 10dB
Output Return Loss > 10dB > 10dB > 10dB
CI slots 0 2 0 2
DC Operating voltage 12 ± 1VDC 12 ± 1VDC 12 ± 1VDC 12 ± 1VDC
DC Current consumption (typ.) 700mA 900mA 1000mA 1200mA
Humidity - operating 20 80% 20 80% 20 80% 20 80%
Humidity - storage 10 90% 10 90% 10 90% 10 90%
Temperature - operating -10 +50°C -10 +50°C -10 +50°C -10 +50°C
Temperature - storage -20 +70°C -20 +70°C -20 +70°C -20 +70°C
MECHANICAL
Dimensions product (H x D x W) 17 x 162 x 185mm 24 x 162 x 185mm 17 x 162 x 185mm 24 x 162 x 185mm
Packing QTY 1 1 1 1
Weight (kg) 0.41kg 0.44kg 0.43kg 0.46kg

PAL HD downscale - 2 x CI slot and IP backend modules





TDX quad PAL HD downscale

These modules take any HD service from the TDX pool, scale the service down to SD format, modulate it to a PAL signal and distribute it in a PAL network. You can distribute 4 PAL services / TV programmes from each module, equal to 24 PAL services from one cabinet.

The PAL HD downscale module comes in 2 versions: a Free-to-Air version and a CI version with 2 CI slots for decrypting content or services. AC3 support is possible with the addition of an AC3 activation licence.

Triax IP backend

This is an output module for the transmission of digital video, audio and miscellaneous data, encapsulated within one or more MPEG2/DVB single programme transport streams. Besides the backend module the package consists of a AUX-TS-Loop module and an SFP RJ45 (small form factor pluggable) module. IP licences are required.

Features:

- IP transmission of up to 80 MPEG2/DVB SPTS
- Configurable ratio of 3-7 TS packets / MTU
- Configurable output priority for each output SPTS
- RTP option
- 2 x CI slots complying to EN 50 221
- Hotswappable



TDX Backend - PAL HD FTA downscale





TDX Backend - PAL HD downscale - 2Cl Art. No. 492053





TDX Backend - IP - 2CI

TDX Backend - 2CI

Art. No. 492070

5702664920704

EAN Number

Art. No. 492072 EAN Number 5702664920728




x 1

PAL HD downscale - $2 \times CI$ slot and IP backend modules

TDX – IP backend





-				
Туре:	TDX Backend PAL HD FTA	TDX Backend PAL HD	TDX Backend 2CI	TDX Backend IP - 2CI
	downscale	downscale - 2Cl	201	IP - 201
Art. no.	492052	492053	492070	492072
CHARACTERISTICS	492032	492000	492070	492072
Crominance/luminance delay	< 80ns/m	< 80ns/m		
FIT	< 00115/111	< 00115/111		No EIT - must be obtained
				via native IP OUT
Differential Gain	< 8%	< 8%		
Differential Phase	< 8°	< 8°		
Output Audio S/N Ratio	50dB	50dB		
Output level adjustment	+317dB	+317dB		
Output Level System Output Video S/N Ratio	103dBµV ≥ 57dB	103dBµV		
Output Video S/N Ralio Output format	≥ 2/0B	≥ 57dB		MPEG-2/DVB compliant
Output format				SPTS UDP/IP
				multicast via GbE
Picture carrier stability	< ±30kHz	< ±30kHz		
Sound sub carrier	5.5/5.74/6.0/6.5MHz	5.5/5.74/6.0/6.5MHz		
Spurious Signals	> 60dB	> 60dB		
FREQUENCY				
Channel Raster	7, 8MHz	7, 8MHz		
Frequency step	250kHz	250kHz		
Output frequency range	47 - 862MHz	47 - 862MHz		
RETURN LOSS				
Output Return Loss	> 10dB	> 10dB		
ELECTRICAL				
Luminance non-linearity	< 8%	< 8%		
Impedance			75Ω	75Ω
OPERATIONAL	_			-
CI slots	0	2	2	2
DC Operating voltage DC Current consumption (typ.)	12 ± 1VDC 1600mA	12 ± 1VDC 1800mA	12 ± 1VDC 600mA	12 ± 1VDC < 600mA
Humidity - operating	20 80%	20 80%	20 80%	20 80%
TV-norm		D/K), Secam	20 00 %	20 00 %
Humidity - storage	10 90%	10 90%	1090%	10 90%
Output protocol			3-7:1 TS / IP packet	ratio (configurable via
· · ·			GUI), RTP (op	tional via GUI)
Temperature - operating	-10 +50°C	-10 +50°C	-10 +50°C	-10 +50°C
Temperature - storage	-20 +70°C	-20 +70°C	-20 +70°C	-20 +70°C
MECHANICAL				
Dimensions product (H x D x W)	17 x 162 x 185mm	24 x 162 x 185mm	24 x 162 x 185mm	24 x 162 x 185mm
Packing QTY	1	1	1	1
Weight (kg)	0.43kg	0.46kg	0.22kg	0.22kg

TRIAX® TDX

fibre modules & software





TDX Software IP input/output functionality

Create your own array of services / TV programmes from the TDX pool, distribute them on an IP data stream and define them in the TDX tool. No output module is needed, so long as more than 1 TS package per UDP package or RTP protocol is required – otherwise, an IP backend is required and you will need a licence key

> TDX SFP Module Fibre LC 1310nm

Art. No. 492088

5702664920889

EAN Number

[EOLT - 1324-02XX plug]

containing the rights to the number of services needed. The licence keys are available in packages of 4 and 12 (96 IP out) IP services in each package. When the services are distributed in IP format, you will also need an SFP transceiver and a corresponding fibre or RJ45 cable.





Туре:	TDX SFP Module - Copper RJ45 - EOLT - C12-02 plug	TDX SFP Module - Fibre LC 850nm EOLT - 8512 MXX plug	TDX SFP Module - Fibre LC 1310nm [EOLT - 1324-02XX plug]
Art. no.	492086	492087	492088
OPERATIONAL			
Data rate	1000	1000	1000
Reaching area	100m	550m	2.000m
MECHANICAL			
Packing QTY	1	1	1
Remarks	Copper SFP (RJ45)	Fibre LC - 850 nm	Fibre LC - 1310 nm

 \searrow

x 1

TRIAX® TDX software licence


TDX – IP-in and IP-out



TDX IPTV-in 4 service -

Start

Start














Art. No. 418045 \square **EAN Number** x 1 5702664180450

TDX IPTV-in 12 service -

TDX IPTV-in 12 service -Expand Art. No. 418046



TDX IPTV-out 12 service -Start Art. No. 418040

EAN Number 5702664180405

\square x 1

TDX IPTV-out 12 service -Expand Art. No. 418041 $\langle \rangle$



TDX Samsung DRM backend license

Art. No. 418073 **EAN Number** x 1 5702664180733

TDX - IP-in and IP-out



TDX Alternative EIT source

Art. No. 418050 **EAN Number** 5702664180504



 \square



TRIAD

TDX PAL AC3 activation license

Art. No. 418051 **EAN Number** 5702664180511

x 1

TDX SimulCrypt 24 service

Art. No. 418072 **EAN Number** 5702664180726

\square x 1



Art. No. 418062 **EAN Number** 5702664180627

\sum x 1

TRIAX

Art. No. 418063



EAN Number 5702664180634



TRIAX® TDX

accessories & spare parts





TDX IPTV EPG Server

The EPG Server extracts data from DVB-S, DVB-C and DVB-T front end modules, generating different XML formats to support IP set-top boxes, IP TVs and middleware solutions.

TDX Redundant Power Supply

The TDX redundant power supply provides you with a high degree of power assurance in connection with your TDX headend system.

The redundant power supply uses two identical TDX Power supplies mounted in a mechanical frame. This means only one power supply in stock to support TDX and redundant power supply installations. If one power supply unit breaks down the other unit instantly takes over and thereby prevents an interruption of the supply of power. The damaged power supply can be changed without disconnecting the working unit from the power.





TRIAX® TDX accessories & spare parts



TDX Controller



Art. No. 492000 EAN Number 5702664920001



TDX SD card

Art. No. 492084 EAN Number 5702664920841



TDX Double fan kit

Art. No. 775365 EAN Number 5702667753651



TDX power supply

Art. No. 492005 EAN Number 5702664920056

TRIAX® TDH800 cabinet

the all-rounder with innovative pool technology





TDH 800

The TDH 800 headend is ideal for those looking for a flexible, compact and reliable solution, with a range of input and output modules for all popular TV distribution formats.

If you need additional features such as multi unit or IP-in/out, then please select the TDX headend.

Perfect for

- Hotels
- Large multi-family houses
- Small settlements

Key features

- Fully configurable thanks to pool technology
- More programme channels by multiplexing
- Configuration via web interface



TDH 800 Cabinet - Main Unit

Art. No. 692890 EAN Number 5702666928906



TRIAX® TDH800 cabinet

main unit for TDH range of modules



Туре:	TDH 800 Cabinet Main Unit
Art. no.	692890
CHARACTERISTICS	
External test point	F-connector
Max. LNB control	4 x 305mA
Output level max. @ 60 dB IMD	
- 24 combined channels	93dBµV
Test point	- 20dB
DiSEqC level FREQUENCY	
Frequency range (RF OUT)	47-862MHz
RETURN LOSS	
Return loss (RF OUT)	> 10dB
ELECTRICAL	
Impedance	75Ω
OPERATIONAL	
Humidity - operating	20 to 80%
Humidity - storage	10 to 90%
AC Supply voltage	190-260 (50/60 HZ IEC320 1.8m cable)VAC
Power Consumption (typ.)	280 (min 20)W
Temperature - operating	-10 to +50°C
Temperature - storage	-20 to +70°C
CONNECTORS	
External RF OUT	F-connector
PC interface	RJ 45
MECHANICAL	
Dimensions product (H x D x W)	265 x 240 x 440 mm
Packing QTY	1pcs
Remarks	

TRIAX® TDH800 input modules

DVB-S/S2 - DVB-T/T2 - HDMI and AV frontend encoder module






DVB-S/S2

This frontend module is an input module for the reception of digital satellite signals in a TDH 800 headend system. The module can receive a complete transponder, and all services on the chosen frequency can be transferred to the IP-pool.

The DVB-S/S2 frontend module includes an IF tuner with antenna loop through and a QPSK/8PSK demodulator with serial transport stream input to the TDH 800 headend system.

DVB-T/T2

This frontend module is an input module for the reception of both T and T2 digital terrestrial signals. The module can receive a complete terrestrial mux and send all services in the mux to the IP-pool.











TDH 815 Frontend HDMI module



Art. No. 692830 **EAN Number** 5702666928302



TRIAX[®] TDH800 input modules DVB-S/S2 - DVB-T/T2 - HDMI and AV frontend encoder module

HDMI & AV

The AV encoder module converts analogue video (CVBS) and the HDMI encoder module converts digital signals from a set top box, a DVD player, a camera or other sources, into a MPEG2 or MPEG4 data stream.

This data stream is then available in the IP-pool and can be sent out on all TDX output modules.

A 15 pol Sub-D or HDMI cable can be used to connect the source to the AV- or HDMI module is also available.

Type: Art. no.	TDH 800 Frontend DVB-S/S2 [QPSK/8PSK] 692820	TDH 800 Frontend DVB-T/T2 [COFDM] 692823	TDH 800 Frontend AV encoder module 692880	TDH 815 Frontend HDMI module 692830
CHARACTERISTICS	072020		092000	072000
Audio embedded			AAC, 48 kHz/ MPEG-2(L1), Stereo	AAC, 48 kHz/ MPEG-2(L1), Stereo or AC3 pass through
Code rates DVB-T Code rates DVB-T2 Constallations DVB-T Constallations DVB-T2		1/2, 2/3, 3/4, 5/6, 7/8 1/2, 2/3, 3/4, 5/6 QPSK, 16QAM, 64QAM QPSK, 16 QAM, 64 QAM, 256 QAM		
DiSEqC level	1.1			
FFT mode DVB-T FFT mode DVB-T2 Input audio level		2K, 8K 1K,2K,4K,8K,16K,32K	2.4Vpp	
Input level	5575dBµV	4575dBµV	1.01/	
Input video level Input Video S/N Ratio			1.0Vpp > 52dB	
Input video standards			PAL, Secam	480i30; 480p60; 576i25; 576p50; 720p50/60; 1080p25/30; 1080i25/30
LNB LO/HI programmable	0/22kHz			
Output Type				MPEG (Serial) transport stream (LVDS)
Output Video Codec Output Video Codec Settings (CBR)			MPEG-2, MPEG-4 1, 2, 2.5, 3, 4, 5, 6, 7, 8, 9, 10 MbpsMbps	MPEG-2, MPEG-4 311 á 1Mbps
Scan Resolution FREQUENCY			525, 625 Pixel	
Bandwidth		7/8MHz	50,00,00011	
Audio frequency response Input frequency range	9502150MHz	VHF 177.5-226.5 MHz UHF 474 - 858MHz	50 - 20.000Hz	
GAIN				
Input noise figure RETURN LOSS		< 7.0dB		
Input return loss ELECTRICAL	> 10dB	> 6dB	> 26dB	
Harmonic Distortion Max. Impedance Input Audio Impedance Physical Interface	75Ω	75Ω	< 1.0% 75Ω 10 ± 1kΩ CVBS	
OPERATIONAL DC Operating voltage	12VDC	12VDC		12 ± 1VDC
DC Operating voltage DC Current consumption (typ.) Humidity - operating Temperature - operating CONNECTORS	OFF 150/ ON 450mA 2080% -10+50°C		20 to 80% -10 to +50°C	 < 320mA 2080% -10+50°C
Connector Type Number of inputs MECHANICAL	F-female 1	F-female 1	15pol Sub-D 1 x AV-signal	HDMI female (A) 1x HDMI
Dimensions product (H x D x W) Packing QTY	32 x 132 x 50mm 1	29 x 132 x 50mm 1	29 x 126 x 53mm 1	29 x 126 x 53mm 1

quad PAL HD downscale - FTA or with 2 x CI slot





TDH800 quad PAL HD downscale

These modules take any HD service from the IP-pool, scale it down to SD format, modulate it to a PAL signal and distribute it in a PAL network. You can distribute 4 PAL services / TV programmes from each module, equal to 24 PAL services from one cabinet.

The PAL HD downscale module comes in 2 versions: a Free-to-Air version and a CI version with 2 CI slots for decrypting content or services. AC3 support is possible with the addition of an AC3 activation licence.



PAL-HD Downscale FTA Art. No. 692852 EAN Number 5702666928524

TDH 848 Backend -



PAL-HD Downscale CI Art. No. 692853 EAN Number 5702666928531

TDH 849 Backend -





Art. No. 692870 EAN Number 5702666928708





CI only

Туре:	TDH 848 Backend PAL-HD Downscale FTA	TDH 849 Backend PAL-HD Downscale Cl
Art. no.	692852	692853
CHARACTERISTICS		
Output Audio S/N Ratio	50dB	50dB
Output Level System	103dBµV	103dBµV
Output Video S/N Ratio	≥ 57dB	≥ 57dB
Sound sub carrier	5.5/5.74/6.0/6.5MHz	5.5/5.74/6.0/6.5MHz
Spurious Signals	> 60dB	> 60dB
FREQUENCY		
Channel Raster	7, 8MHz	7, 8MHz
Frequency step	250kHz	250kHz
Output frequency range	47 - 862MHz	47 - 862MHz
RETURN LOSS		
Output Return Loss	> 10dB	> 10dB
ELĖCTRICAL		
Impedance	75Ω	75Ω
OPERATIONAL		
CI slots	0	2
DC Operating voltage	12 ± 1VDC	12 ± 1VDC
DC Current consumption (typ.)	1600mA	1800mA
Humidity - operating	20 80%	20 80%
Humidity - storage	10 90%	10 90%
Temperature - operating	-10 +50°C	-10 +50°C
Temperature - storage	-20 +70°C	-20 +70°C
CONNECTORS		
Connector Type	F-female	F-female
MECHANICAL		
Dimensions product (H x D x W)	17 x 162 x 185mm	24 x 162 x 185mm
Packing QTY	1	1

Triax 2 x CI backend

The 2 x CI backend module enables you to take several services depending on CAM module from the IP pool, decrypt them and loop them back in decrypted form to the pool.

Type:	TDH 847 2CI Backend
Art. no.	692870
ELECTRICAL	0,2010
Impedance OPERATIONAL	75Ω
CI slots	2
DC Operating voltage	12 ± 1VDC
DC Current consumption (typ.)	600mA
Humidity - operating	20 80%
Humidity - storage Output protocol	10 90%
Temperature - operating	-10 +50°C
Temperature - storage	-20 +70°C
CONNECTORS	E formale
Connector Type MECHANICAL	F-female
Dimensions product (H x D x W)	24 x 162 x 185 mmmm
Packing QTY	1

quad QAM backend module DVB-C in FTA or with 2 x CI slot






TDH800 quad COFDM

These backend modules are output modules that enable you to create up to 4 muxes of services / TV programmes which are available from the IP-pool. The services are distributed in a COFDM data stream. The services can be combined so that the bandwidth of each output mux is used in an optimal way. The mux bandwidth monitor function in the service tool ensures that you don't overload the bandwidth and cause problems with the transmission.

TDH800 quad QAM

These backend modules are output modules that enable you to create up to 4 muxes of services / TV programmes which are available from the IP-pool. The services are distributed in a QAM data stream. The services can be combined so that the bandwidth of each output mux is used in an optimal way. The mux bandwidth monitor function in the service tool ensures that you don't overload the bandwidth and cause problems with the transmission.



×1



quad COFDM backend module DVB-T in FTA or with 2 x CI



Туре:	TDH 800 Backend - COFDM	TDH 800 Backend - COFDM -2CI	TDH 800 Backend - OAM	TDH 800 Backend - OAM - 2Cl
Art. no.	692860	692861	692855	692856
CHARACTERISTICS	092000	092001	092000	092030
Carrier supported	2K	2K		
Guard Interval	1/32, 1/16, 1/8, 1/4	1/32, 1/16, 1/8, 1/4		
Deinterleaver	1/02, 1/10, 1/0, 1/1	1,02, 1, 10, 1,0, 1,	=12	=12
Reed Solomon decoder	204 byte mode	204 byte mode	204, 188, t=8	204, 188, t=8
MER	≥ 35.0dB	≥ 35.0dB	≥ 38.0dB	≥ 38.0dB
Output Level System	90.0 ± 1.5dBµV	90.0 ± 1.5dBµV	90.0dBµV	90.0dBµV
Output QAM Modes	16 QAM, 64 QAM,	16 QAM, 64 QAM,	16 QAM, 32 QAM,	16 QAM, 32 QAM,
	QPSK	QPSK	64 QAM, 128 QAM,	64 QAM, 128 QAM,
			256 QAM	256 QAM
Output symbol rate			3.157.2Mbit/s	3.157.2Mbit/s
Spurious Signals	> 60dB	> 60dB	> 60dB	> 60dB
Roll-Off Factor			15%	15%
TER - FEC rate	1/2, 2/3, 3/4, 5/6, 7/8	1/2, 2/3, 3/4, 5/6, 7/8		
FREQUENCY				
Channel Raster	7, 8, 8.5MHz	7, 8, 8.5MHz	7, 8, 8.5MHz	7, 8, 8.5MHz
Frequency step	250kHz	250kHz	250kHz	250kHz
Output frequency range	50.5 - 858MHz	50.5 - 858MHz	50.5 - 858MHz	50.5 - 858MHz
RETURN LOSS				
Output Return Loss	> 10dB	> 10dB	> 10dB	> 10dB
ELECTRICAL				
Impedance	75Ω	75Ω	75Ω	75Ω
OPERATIONAL				
CI slots	0	2	0	2
DC Operating voltage	12 ± 1VDC	12 ± 1VDC	12 ± 1VDC	12 ± 1VDC
DC Current consumption (typ.)	1000mA	1200mA	700mA	900mA
Humidity - operating	2080%	2080%	2080%	2080%
Humidity - storage	1090%	1090%	1090%	1090%
Temperature - operating	-10+50°C -20+70°C	-10+50°C -20+70°C	-10+50°C -20+70°C	-10+50°C -20+70°C
Temperature - storage CONNECTORS	-20+70 6	-20+70 6	-20+70 C	-20+/0 6
	⊑ fama ala	E fama ala	⊑ faura a la	E fama ala
Connector Type MECHANICAL	F-female	F-female	F-female	F-female
Dimensions product ($H \times D \times W$)	17 x 162 x 182mm	24 x 162 x 182mm	17 x 162 x 185mm	24 x 162 x 185mm
Packing QTY	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	24 X 102 X 18211111 1	1 1	24 X TOZ X TOUTITT 1
r acking QTT	I	I	1	1

CAS – Conditional Access Systems

for hospitality and CATV Solutions





Conditional Access Turn-Key Solutions

TRIAX is your reliable partner for turn-key solutions, supporting headend operators with everything they need for digital TV projects.

Plug & Play Hardware

All our CAS hardware is plug & play and can be easily installed with little prior knowledge. Configuration is downloaded from our central server and a continuous backup ensures data integrity at all times. Faulty hardware simply needs to be exchanged – its replacement will automatically receive the same configuration with no additional steps required.

Security

We're committed to keeping content secure, and we've developed a set of countermeasures and standby technologies to allow continuity. Control words to protect broadcast content generated by scramblers in the headend are secured along the whole signal chain. Unique keys branded into secure chipsets together with watermarking technology effectively prevent control word sharing on all scales. Copy protection is a must for a Conditional Access System.

CAS Hospitality

This solution has been specifically designed for the needs of the hospitality sector. Each guest house, clinic or hotel needs to offer value-added TV services and whether in limited budgets or green field deployment of state-of-theart TV services, TRIAX is the key component for successful access control. Hospitality operators are able to offer linear TV services and Video-On-Demand to their guests while retaining full control over guests' demands and guarding against piracy.

Content in any network infrastructure can be secured and controlled with one single chassis CAS Server in the headend. Using any type of cabling (coaxial, twisted pair or even wireless), and any type of transport (DVB-C/T or IP-based), the headend controls both one-way (broadcast) and two-way transport networks. Existing TV sets can be used by adding a Common Interface module. More functionality will be available with a set top box. Every employee has their unique interface: a receptionist handles the payment and controls the guest subscription accordingly, a technician or caretaker maintains and manages the respective smartcards / devices of the rooms. A manager has full control and observes all actions, including those executed in the past. Easy and effortless management of the overall system without the need for specialists is therefore possible.



Features:

- Supports room management for up to 500 rooms
- Room messaging (On-screen messages)
- High-end conditional access system (CAS)
- Compatible with QAM, COFDM and IP
- Data stored at a secure TRIAX database (no backup necessary)
- Controlled by CAS Management Software or network based interface
- Pay per channel, TV client, provisioning, etc.
- Any client device: TV with CI interface or set-top box
- Smartcard or cradles licenses possible
- Hospitality & hotel chains management (on request): Master account for managing thousands of hotels uniformly
- Easy to use reception mode
- Easy integration into your PMS system (on request)

CAS – Conditional Access Systems

for hospitality and small CATV Solutions



TRIAX[®] CM 01

1 channel modulators






TRIAX modulators

CM series:

TRIAX CM modulators modulate AV signals from a camera, video or set top box to a VHF channel (CM 01V), UHF channel (CM 01U) or UHF channel with integrated amplifier (CM 01UA).

- Multi-standard
- Easy programming
- PLL locked frequency
- Built-in power supply

CM 01U [UHF] modulator



EAN Number 5702663001022

CM 01UA [UHF] modulator with amplifier



Art. No. 300116 EAN Number 5702663001169

CM 01V [VHF] modulator



EAN Number 5702663001015

Art. No. 300101

TFM01

The TRIAX Fullband Modulator TFM01 allows you to mix the output from any normal VCR/DVD-Player, camera, etc. with a composite output signal and enjoy it on any standard PAL TV-set in your household. Due to the full VHF/UHF coverage of this modulator you can be sure always to find a TV channel in your home system that is free for use and interference.

MOD 101

The MOD 101 is a digital modulator with one high definition HDMI input (1080P, MEPG4) and a full range COFDM modulator (MOD 101T) or full range QAM modulator (MOD 101C).



MOD 101C HDMI-QAM

Art. No. 300126 EAN Number 5702663001268



MOD 101T HDMI-COFDM

Art. No. 300125 EAN Number 5702663001251



Art. No. 300112

EAN Number 5702663001121

TRIAX® CM 01 1 channel modulators with amplifier

Туре:	CM 01V [VHF] modulator	CM 01U [UHF] modulator	CM 01UA [UHF] modulator with amplifier		MOD 101T HDMI-COFDM	TFM01 Fullband Modulator
Art. no.	300101	300102	300116	300126	300125	300112
CHARACTERISTICS Audio Compression				MPEG-1 Audio Layer II (ISO/ IEC 11172-3)	MPEG-1 Audio Layer II (ISO/ IEC 11172-3)	
Audio Input Code rate	0.5 V RMS	0.5 V RMS	0.51.0 V RMS		Stereo, HDMI 1/2, 2/3, 3/4, 5/6, 7/8	
COFDM Constellation					DVB-T QPSK/16 QAM/ 64 QAM	/
Guard Interval					1/4, 1/8, 1/16, 1/32	
MER Number of carriers Input level			max. 70 dBµV	>36dB 75 - 90dBµV	>36dB 2K / 8K 90dBµV	
Output level @ 60 dB IMD Video Compression	max. 80 dBµV	max. 80 dBµV	7282 dBµV	75 - 90dBµV H.264/AV	90dBµV H.264/AC	72 - 82 dBµV
Video Input . CVBS Video resolution	1.0 Pal-B	1.0 Pal-G	0.81.0 Pal-G	HDMI Up to 1080p @30HzPixel	HDMI Up to 1080p @30HzPixel	0.81.0Vpp
Modulator type FREQUENCY]	Double side ban	d	(WOOTIZI IXCI	WOOTIZITIKEI	
Gain from out 1/out 2			2 @ Out1 10 @ Out2 dB			2 @ Out1 10 @ Out2 dB
Bandwidth Frequency range Output attenuation RETURN LOSS	175335MHz 010 dB	470860MHz 010 dB	470860MHz 010 dB	6/7/8MHz 100 - 860MHz	6-8MHz 100-860MHz	MHz 010 dB
LCN PID settings				Up to 1023 PMT/Video & Audio / PCR	Up to 1023 PMT/Video & Audio / PCR	
PSI Screen Resolution					HID/ONID/ P.D.S./TS ID 1024x768 / 1280x/720 /	
		1280X600 / 1280x/720 / 1280x768 / 1360x768 / 1366x768				
Through loss ELECTRICAL	4.0dB	4.0dB				
Impedance OPERATIONAL DC Operating voltage	75Ω	75Ω	75Ω	75Ω 12VDC	75Ω 12VDC	75Ω
External PSU AC Supply voltage Power Consumption (typ.) CONNECTORS	230VAC 3.0W	230VAC 3.0W	230VAC 3.5W	Included 8W	8W	230VAC 3.5W
Connector IN Connector OUT Input connector	1 x F-female 1 x F-female	1 x F-female 1 x F-female	1 x F-female 2 x F-female	HDMI female F-female HDMI, F-terrestrial loop through	HDMI female F-female Video/Audio: HDMI Type A	1 x F-female 1 x F-female
MECHANICAL Product Depth Product Width Product Height Weight (kg) Display	54mm 174mm 75mm L	54mm 174mm 75mm	54mm 174mm 75mm	150mm 150mm 36.5mm 0.48kg LCD panel and	150mm 150mm 36.5mm 0.48kg LCD panel and	0.5kg Buttons
Packing QTY Remarks	1 Use SCA	1 ART cable art. nc	1 . 300743	buttons 1	buttons 1	Use SCART cable art. no. 300743



Contact triax.com / contact TRIAX is a global supplier of reliable, innovative products and solutions for the reception and distribution of video, audio and data signals.

Our Products are used in homes, businesses and operator networks by broadcasters, satellite, cable and telecom operators.

Our Solutions combine our hardware and software expertise to deliver value to hospitality and related markets, through a partner network of system integrators, large installers and operators.

TRIAX's headquarters, production and R&D base is in Denmark. With 9 international sales subsidiaries we operate in more than 60 distributor countries. The TRIAX team consists of 300 employees and is owned by Polaris Private Equity.

See www.triax.com for further info.

Copyright © 2018 TRIAX. All rights reserved. The TRIAX Logo and TRIAX, TRIAX Multimedia are registered trademarks or trademarks of the TRIAX Company or its affiliates.

The TRIAX portfolio is constantly changing and growing so this catalogue cannot be complete at all times. Please refer to our website and your sales representative for an update. All specification in this catalogue subject to change without further notice.

