

# SW-HF5.1 6000

200-watt 5.1 Wood Surround System



## Enjoy your home music just like in concert hall!!

Enjoy a home theater experience or exciting games with the Genius six-piece SW-HF5.1 6000 Surround Sound System. With the **SW-HF5.1 6000** from Genius, you experience all-in-one surround sound in a very solid and elegant, wooden home theater system.

This six-piece wood speaker system combines a 100 watt subwoofer with a built-in 8" long-throw driver to provide deep rich bass performance and five 20 watt two-way satellites to deliver a total power output of 200 watts (RMS). A remote control is available to control the volume, and set the self-EQ for the subwoofer/center/front/surround in order to create the ultimate surround effect. The various audio inputs let you connect to a DVD, TV, and other stereo devices easily. And the LCD display shows every movement digitally. Connection is easy and simple. All of the **SW-HF5.1 6000** speakers and the cables are color-coded and clearly labeled for easy setup.

When you're sitting in the living room with the remote control, it'll be just like having your own personal theater with this speaker system. So bring true sound to life with the Genius **SW-HF5.1 6000** surround speaker system and enjoy your music just like in a concert hall.

### Features:

- Six-piece wooden home theater speaker system with a total of 200 watts RMS output power
  - Subwoofer: 100 watts
  - Center/Front/Surround speakers: 20 watts per channel
- LCD display shows full function
- Create 5.1 surround sound for music, movies and video games
- Great for working with a DVD player, Game console and TV/MP3/CD players
- Remote control included



LCD display



Functions



### Dates available:

- ◆ Sample: Mar. 28, 2008
- ◆ Mass Production: Mar. 28, 2008

# SW-HF5.1 6000

200-watt 5.1 Wood Surround System



## Product specification

- Power Rating : 200 watts RMS  
Subwoofer: 100 watts  
Satellites and Center: 20 watts each at THD10%
- Drivers :  
Subwoofer: 8" 6 ohm woofer  
Front Speaker: 4" 8 ohm Full Range and 1" 8 ohm Dome Tweeter  
Rear Speaker: 4" 8 ohm Full Range and 1" 8 ohm Dome Tweeter  
Center: Two 4" 4 ohm Full Range and 1" 8 ohm Tweeter
- Fuse:  
AC 250V/2.5A (Local Voltage: 220~240V)  
AC 125V/4A (Local Voltage: 100~120V)
- AC IN: AC transformer built-in
- Frequency Response: 40Hz ~ 20KHz
- Signal-to-Noise Ratio: 80 dB
- Audio Input:  
Six RCA Audio Input jacks for 5.1 channel DVD player  
Three pairs of RCA jack for two-channel audio sources, such as TV, PC, CD players, MP3 players and game consoles.
- IR Receiver: Built-in to subwoofer
- Amplifier: Built-in to Subwoofer
- Dimensions(W x H x D):  
Subwoofer: 213 x 410 x 360 mm  
Front Speaker: 140 x 233 x 151 mm  
Remote control: 48 x 149 x 17mm  
Center: 332 x 163 x 151 mm  
Surround Speaker: 140 x 233 x 151 mm
- Remote Control:  
Battery: Two AAA batteries (included)

## Package Contents:

- One subwoofer
- Two front speakers
- One remote control
- One 6RCA to 6RCA cable
- Three converter cables
- One center speaker
- Two surround speakers
- Five bare wires
- One 3.5mm to RCA cable
- Two AAA batteries

## Applications:



Movies/TV



Music



Game console

# SW-HF5.1 6000

200-watt 5.1 Wood Surround System



## Comparison data:

Model Name	SW-HF5.1 5000	SW-HF5.1 5005	SW-HF5.1 6000
Image			
<b>Specifications</b>			
Total RMS (Watt)	150	150	200
Woofers	75	75	100
Center	15	15	20
Front	15 x 2	15 x 2	20 x 2
Rear	15 x 2	15 x 2	20 x 2
<b>Driver</b>			
Woofers	6.5" woofer	6.5" woofer	8" woofer
Center	2 x 4" full-range + tweeter	2 x 4" full-range + tweeter	4" full-range + tweeter
Front	4" full-range + tweeter	4" full-range + tweeter	4" full-range + tweeter
Rear	3" full-range + tweeter	3" full-range + tweeter	4" full-range + tweeter
Frequency Response	20~20K Hz	40~20K Hz	40~20K Hz
Signal-to-Noise ratio	85dB	85dB	80 dB
<b>Function</b>			
Master Volume	Y	Y	Y
Center Volume	Y	Y	Y
Surround Volume	Y	Y	Y
Subwoofer Volume	Y	Y	Y
Mute	Y	Y	Y
Aux Input	3	3	3
Power Source	AC transformer built-in	AC transformer built-in	AC transformer built-in
Color Available	Beech Wood and Pear Wood	Silver and Cherry wood	Cherry wood
<b>Front Panel Controls</b>			
Stand-By button	Y	Y	Y
Master Volume Switch	Y	Y	Y
Center/Woofers/Surround Switches	Y	Y	Y
Input Source Selection buttons	DVD, TV, GAME and CD/MP3	DVD, TV, GAME and CD/MP3	DVD, TV, AUX 1 and AUX 2
Mute button	Y	Y	Y
Front Panel LED colors	Blue lights, red for Mute	Blue lights, red for Mute	-
LCD Display	-	-	Y
<b>IR Controls</b>			
Stand-By	Y	Y	Y
Master Volume up/down	Y	Y	Y
Mute	Y	Y	Y
Input Source Selection	Y	Y	Y
<b>Connectivity on the back subwoofer</b>			
Six-channel Input 1 (Six RCA jacks)	Y	Y	Y
Six-channel Input 2 (9-pin Din jack)	Y	-	-
Two-channel Input (RCA jacks)	3	3	3
Power on/off switch	Y	Y	Y
Output (Spring Tags)	Y	Y	Y
<b>Dimensions (mm)</b>			
Subwoofer	220 x 412 x 344	220 x 424 x 332	213 x 410 x 360
Center Speaker	332 x 142 x 155	332 x 163 x 153	332 x 163 x 151
Front Speaker (each)	140 x 217 x 165	140 x 233 x 163	140 x 233 x 151
Rear Speaker (each)	120 x 197 x 140	120 x 213 x 138	140 x 233 x 151
<b>Packing</b>			
20°CY / 40°CY / 40HQ	255 / 540 / 540 sets	246 / 520 / 640 sets	250 / 515 / 615 sets