# **ENFORCER®**

# **Electric Door Strike**

## TWO MODELS TO CHOOSE FROM:

SK-990A Fail-Secure (Door unlocked with power connected)
SK-990B Fail-Safe (Door locked with power connected)

#### **FEATURES:**

 The ENFORCER Electric Door Strikes convert cylindrical lock sets to an electronic access controlled locking system.

 Can be used on virtually any cylindrical door locking system.

• Use of a digital keypad with the unit assures high security without the need of a key.

 Easily connects to SECO-LARM's SK-983A Electronic Keypad.

• Suitable for office-type applications.

CE approved.

Baked painted finishing.

• Fail-Secure (SK-990A) units are perfect for entrance door installations.

 Fail-Safe (SK-990B) units are perfect for emergency door and escape door installations.

#### **SPECIFICATIONS:**


	SK-990A	SK-990B
Туре	Fail-Secure	Fail-Safe
Circuit Type	N.O.	N.C.
Input Voltage	10-14VDC	10-14VDC
Current	800mA	165mA
Coil Resistance	$14\Omega$	76Ω
Polarity	None	None
Weight	350g	350g

For more information, contact

SECO-LARM® U.S.A., Inc. 16842 Millikan Avenue

Irvine, CA 92606

### **DIMENSIONS:**



Tel: 1-800-662-0800 (domestic U.S. & Canada)
Tel: 1-949-261-2999 (California & international)

Fax: 1-949-261-7326 Email: info@seco-larm.com