

2002 SONY MOBILE PRODUCT GUIDE



CDX-565MXRF Compact Disc Changer System

- Electronic Shock Protection (ESP)
 - MP3 & CD-RW Playback
 - Built-in RF Modulator
 - 9 selectable RF frequencies
 - 5 selectable output levels
 - Super Suspension Shock Isolation
 - XA-250 10-disc Magazine
 - Supplied Low-profile Wired Commander (RM-X83RF)
 - Supplied Wireless Remote (RM-X84RF)
 - CD TEXT®
 - D-Bass
 - 8X Oversampling
 - 1-Bit D/A Converter
- Indicate step-up

CD Changer

System	Compact disc digital audio system
Laser Diode Properties	
Material	GaAlAs
Wavelength	780 nm
Emission Duration	Continuous
Laser output power	Less than 44.6 μ W*
* This output is the value measured at a distance of 200 mm from the objective lens surface on the Optical Pick-up Block.	
Transmitting frequency	88.3 MHz/88.5 MHz/ 88.7 MHz/88.9 MHz/ 89.1 MHz/89.3 MHz/ 89.5 MHz/89.7 MHz/ 89.9 MHz/(switchable)
Input/output terminals	Wired remote control (8 pin) RF signal (FM) output Power input (3 pin)
Current drain	900 mA (at playback) 900 mA (at disc loading/ejecting)
Operating temperature	-10°C to +55°C (14°F to 131°F)
Dimensions	Approx. 262 × 90 × 185 mm (10 3/8 × 3 5/8 × 7 3/8 in.) (w/h/d)
Mass	Approx. 2.1 kg (4 lb. 10 oz.)

Relay Box

Input/output	Antenna input terminal Antenna output cord CD Changer input cord
Dimensions	40 × 40 × 27 mm (1 5/8 × 1 5/8 × 1 1/8 in.) (w/h/d)
Mass	140 g (5 oz.)


Wired remote (RM-X83RF)/Wireless remote (RM-X84RF)

Dimensions	Wired remote: Approx. 127.5 × 41.5 × 24 mm (5 1/8 × 1 11/16 × 31/32 in.) (w/h/d) Wireless remote: Approx. 52 × 8.5 × 90 mm (2 1/16 × 3/8 × 3 9/16 in.) (w/h/d)
Mass	Wired remote: Approx. 280 g (10 oz.) Wireless remote: Approx. 30 g (1 oz.)
Battery	Wireless remote: Lithium battery (CR2025)

Supplied accessories

- Disc magazine (1)
- Parts for installation and connections (1 set)

Harness Plug Configuration



Plug shown with wires facing viewer.

Pin Number	Wire Color	Description
1	Black	Ground
2	Yellow	Battery
3	Red	Accessory

**CDX-565MXRF
Compact Disc Changer System**

